

On MITL and alternating timed automata

Thomas Brihaye¹ Morgane Estiévenart¹ Gilles Geeraerts²

¹ Université de Mons, Belgium,

² Université Libre de Bruxelles, Belgium

Abstract

One clock alternating timed automata (OCATA) have been recently introduced as natural extension of (one clock) timed automata to express the semantics of MTL [11]. We consider the application of OCATA to problem of model-checking MITL formulas (a syntactic fragment of MTL) against timed automata. We introduce a new semantics for OCATA where, intuitively, clock valuations are *intervals* instead of *single values* in $\mathbb{R}$. Thanks to this new semantics, we show that we can *bound* the number of clock copies that are necessary to allow an OCATA to recognise the models of an MITL formula. Equipped with this technique, we propose a new algorithm to translate an MITL formula into a timed automaton, and we sketch several ideas to define new model checking algorithms for MITL.

1 Introduction

Automata-based model-checking [4, 13] is nowadays a well-established technique for establishing the correctness of computer systems. In this framework, the system to analyse is modeled by means of a *finite automaton* A whose accepted language consists of all the traces of the system. The *property* to prove is usually expressed using a *temporal logic formula* Φ , whose set of models is the language of all *correct executions*. For instance, the LTL formula $\Box(p \implies \Diamond q)$ says that every p -event should eventually be followed by a q -event. Then, establishing correctness of the system amounts to showing that the language $L(A)$ of the automaton is included in the language $\llbracket \Phi \rrbracket$ of the formula. In practice, automata-based model checking algorithms first negate the formula and translate $\neg\Phi$ into an automaton $A_{\neg\Phi}$ that recognises the *complement* of $\llbracket \Phi \rrbracket$, i.e., the set of all *erroneous traces*. Then, the algorithm proceeds by computing the synchronous product $A \times A_{\neg\Phi}$ and check whether $L(A \times A_{\neg\Phi}) = \emptyset$, in which case the system respects the property.

While those techniques are now routinely used to prove the correctness of huge systems against complex properties [3], the model of finite automata and the classical temporal logics such as LTL are sometimes not *expressive* enough because they can model the *possible sequences of events*, but cannot express *quantitative properties about the (real) time elapsing between successive events*. To overcome these weaknesses, Alur and Dill [1] have proposed the model of *timed automata*, that extends finite automata with a finite set of (real valued) clocks. A real-time extension of LTL

is the *Metric Temporal Logic* (MTL) that has been proposed by Koymans [8] and consists in labeling the modalities with time intervals. For instance $\Box(p \implies \Diamond_{[1,2]}q)$ means ‘at all time, each p should be followed by a q -event that occurs *between 1 and 2 time units later*’. Unfortunately, the satisfiability and model-checking of MTL are undecidable on infinite words [7], and non-primitive recursive on finite words [12].

An interesting alternative is the Metric Interval Temporal Logic (MITL), that has been proposed by Henzinger *et al.* [2]. MITL is a syntactic fragment of MTL where singular intervals are disallowed on the modalities. Thanks to this restriction, MITL model-checking is EXPSpace-C, even on infinite words. MITL thus seems a good compromise between *expressiveness* and *complexity*. In their seminal work, Henzinger *et al.* provide a construction to translate an MITL formula Φ into a timed automaton $\mathcal{B}_\Phi$, from which the automaton-based model checking procedure sketched above can be applied. Although this procedure is foundational from the theoretical point of view, it does not seem easily amenable to efficient implementation: the construction is quite involved, and requests that $\mathcal{B}_\Phi$ be completely built before the synchronous product with the system’s model can be explored. Note that an alternative technique, based on the notion of *signal* has been proposed by Maler *et al.* [10]. However the semantics of MITL assumed there *slightly* differs from that of [2], whereas we stick to the original MITL semantics.

Since MITL is a *syntactic fragment* of MTL, all the techniques developed by Ouaknine and Worrell [11] for MTL can be applied to MITL. Their technique relies on the notion of *alternating timed automaton with one clock* (OCATA), an extension of timed automata. Intuitively an OCATA can create several copies of itself that run in parallel and must *all* accept the suffix of the word. For example, Fig. 1 displays an OCATA. Observe that the *arc* starting from ℓ_0 has two destinations: ℓ_0 and ℓ_1 . When the automaton is in ℓ_0 with clock valuation v , and reads a σ , it spawns two copies of itself: the first reads the suffix of the word from (ℓ_0, v) , and the latter from $(\ell_1, 0)$ (observe that the clock is reset on the branch to ℓ_1). Then, every MITL formula Φ can be translated into an OCATA $\mathcal{A}_\Phi$ that recognises its models [11]. The translation has the advantage of being very simple and elegant, and the size of $\mathcal{A}_\Phi$ is linear in the size of Φ . Unfortunately, one cannot bound a priori the number of clock copies that need to be remembered at all times along runs of an OCATA. Hence, OCATA cannot, in general, be translated to timed automata [9]. Moreover, the model-checking algorithm of [11] relies on well-quasi ordering to ensure termination, and has non-primitive recursive complexity.

In the present work, we exploit the translation of MITL formulas into OCATA [11] to devise new, optimal, and – hopefully – elegant and simple algorithms to translate an MITL formula into a timed automaton. To achieve this, we rely on two technical ingredients. We first propose (in Section 3) a novel *interval-based* semantics for OCATA. In this semantics, clock valuations can be regarded as *intervals* instead of *single points*, thus our semantics generalises the standard one [11]. Intuitively, a state (ℓ, I) of an OCATA in the interval-based semantics (where ℓ is a location and I is an interval) can be regarded as an *abstraction* of all the (possibly unbounded) sets of states $\{(\ell, v_1), (\ell, v_2), \dots, (\ell, v_n)\}$ of the standard semantics with $v_i \in I$ for all i . Then, we introduce a family of so-called *approximation function* that, roughly speaking, associate with each configuration C of the OCATA in the interval-based semantics, a set of

configurations that are obtained from C by merging selected intervals in C . We rely on approximation functions to *bound* the number of clock copies that are present in all configurations. Our main technical contribution (Section 4) then consists in showing that, when considering an OCATA $\mathcal{A}_\Phi$ obtained from an MITL formula Φ , combining the interval semantics and a well-chosen approximation function is *sound*, in the sense that the resulting semantics recognises $L(\Phi)$, while requesting only *a bounded number of clock copies*. Thanks to this result, we provide an algorithm that translates the OCATA $\mathcal{A}_\Phi$ into a plain timed automaton that accepts the same language.

From our point of view, the *benefits* of this new approach are as follows. From the *theoretical point of view*, our construction is the first that relies on OCATA to translate MITL formulas into timed automata. We believe our construction is easier to describe (and thus, hopefully, easier to implement) than the previous approaches. The translation from MITL to OCATA is very straightforward. The intuitions behind the translation of the OCATA into a timed automaton are also quite natural (although the proof of correctness requires some technicalities). From the *practical point of view*, our approach allows us, as we briefly sketch in Section 5, to envision *efficient model checking algorithms for MITL*, in the same spirit of the *antichain approach* [5] developed for LTL model checking. Note that the key ingredient to enable this *antichain* approach is the use of *alternating automata* to describe the LTL formula. Our contribution thus lay the *necessary theoretical basis* to enable a similar approach in a real-time setting.

Remark Owing to lack of space, most of the proof are in the appendix.

2 Preliminaries

Basic notions. Let $\mathbb{R}$ ($\mathbb{R}^+$, $\mathbb{N}$) denote resp. the sets of real (non-negative real, natural) numbers. We call **interval** a convex subset of $\mathbb{R}$. We rely on the classical notation $\langle a, b \rangle$ for intervals, where $\langle$ is ($($ or $[$, $\rangle$ is $)$ or $]$, $a \in \mathbb{R}$ and $b \in \mathbb{R} \cup \{+\infty\}$. For an interval $I = \langle a, b \rangle$, we let $\inf(I) = a$ be the *infimum* of I , $\sup(I) = b$ be its *supremum* (a and b are called the *endpoints* of I) and $|I| = \sup(I) - \inf(I)$ be its *length*. We note $\mathcal{I}(\mathbb{R})$ the set of all intervals. Similarly, we note $\mathcal{I}(\mathbb{R}^+)$ (resp. $\mathcal{I}(\mathbb{N})$) the set of all intervals whose endpoints are in $\mathbb{R}^+$ (resp. in $\mathbb{N} \cup \{+\infty\}$). Let $I \in \mathcal{I}(\mathbb{R})$ and $t \in \mathbb{R}$, we note $I + t$ for $\{i + t \in \mathbb{R} \mid i \in I\}$. Let I and J be two intervals, we let $I < J$ iff $\forall i \in I, \forall j \in J : i < j$. For $I \in \mathcal{I}(\mathbb{R})$, $v \in \mathbb{R}$ and $\bowtie \in \{<, >\}$, we note: $I \bowtie v$ iff $\forall i \in I, i \bowtie v$.

Let Σ be a finite alphabet. A *word* on a set S is a finite sequence $s = s_1 \dots s_n$ of elements in S . We denote by $|s| = n$ the length of s . A time sequence $\bar{\tau} = \tau_1 \tau_2 \tau_3 \dots \tau_n$ is a word on $\mathbb{R}^+$ s.t. $\forall i < |\bar{\tau}|, \tau_i \leq \tau_{i+1}$. A *timed word* over Σ is a pair $\theta = (\bar{\sigma}, \bar{\tau})$ where $\bar{\sigma}$ is a word over Σ , $\bar{\tau}$ a time sequence and $|\bar{\sigma}| = |\bar{\tau}|$. We also note θ as $(\sigma_1, \tau_1)(\sigma_2, \tau_2)(\sigma_3, \tau_3) \dots (\sigma_n, \tau_n)$, and let $|\theta| = n$. A *timed language* is a (possibly infinite) set of timed words.

Metric Interval Time Logic. Given a finite alphabet Σ , the formulas of MITL are defined by the following grammar, where $\sigma \in \Sigma$, $I \in \mathcal{I}(\mathbb{R}_\mathbb{N})$:

$$\varphi ::= \top \mid \sigma \mid \varphi_1 \wedge \varphi_2 \mid \neg \varphi \mid \varphi_1 U_I \varphi_2.$$

We rely on the following usual shortcuts $\Diamond_I \varphi$ stands for $\top U_I \varphi$, $\Box_I \varphi$ for $\neg \Diamond_I \neg \varphi$, $\varphi_1 \tilde{U}_I \varphi_2$ for $\neg(\neg \varphi_1 U_I \neg \varphi_2)$, $\Box \varphi$ for $\Box_{[0,\infty)} \varphi$ and $\Diamond \varphi$ for $\Diamond_{[0,\infty)} \varphi$.

Given an MITL formula Φ , we note $Sub(\Phi)$ the set of all subformulas of Φ , i.e. : $Sub(\Phi) = \{\Phi\}$ when $\Phi \in \{\top\} \cup \Sigma$, $Sub(\neg \varphi) = \{\neg \varphi\} \cup Sub(\varphi)$ and $Sub(\Phi) = \{\Phi\} \cup Sub(\varphi_1) \cup Sub(\varphi_2)$ when $\Phi = \varphi_1 U_I \varphi_2$ or $\Phi = \varphi_1 \wedge \varphi_2$. We let $|\Phi|$ denote the size of Φ , defined as the number of U or $\tilde{U}$ modalities it contains.

Definition 1 (Semantics of MITL). *Given a timed word $\theta = (\bar{\sigma}, \bar{\tau})$ over Σ , a position $1 \leq i \leq |\theta|$ and an MITL formula Φ , we say that θ satisfies Φ from position i , written $(\theta, i) \models \Phi$ iff the following holds :*

- $(\theta, i) \models \top$
- $(\theta, i) \models \sigma \Leftrightarrow \sigma_i = \sigma$
- $(\theta, i) \models \varphi_1 \wedge \varphi_2 \Leftrightarrow (\theta, i) \models \varphi_1$ and $(\theta, i) \models \varphi_2$
- $(\theta, i) \models \neg \varphi \Leftrightarrow (\theta, i) \not\models \varphi$
- $(\theta, i) \models \varphi_1 U_I \varphi_2 \Leftrightarrow \exists i \leq j \leq |\theta|$, such that $(\theta, i) \models \varphi_2$, $\tau_j - \tau_i \in I$ and $\forall i \leq k < j$, $(\theta, k) \models \varphi_1$

We say that θ **satisfies** Φ , written $\theta \models \Phi$, iff $(\theta, 1) \models \Phi$. We note $\llbracket \Phi \rrbracket = \{\theta \mid \theta \models \Phi\}$.

Observe that, for all MITL formula Φ , $\llbracket \Phi \rrbracket$ is a timed language and that we can transform any MITL formula in an equivalent MITL formula in *negative normal form* (in which negation can only be present on letters $\sigma \in \Sigma$) using the operators : $\wedge, \vee, \neg, U_I$ and $\tilde{U}_I$.

Example 1. *We can express the fact that ‘every occurrence of p is followed by an occurrence of q between 2 and 3 time units later’ by: $\Box(p \Rightarrow \Diamond_{[2,3]} q)$. Its negation, $\neg(\Box(p \Rightarrow \Diamond_{[2,3]} q))$, is equivalent to the following negative normal form formula: $\top U_{[0,+\infty)}(p \wedge \perp \tilde{U}_{[2,3]} \neg q)$.*

Alternating timed automata. Let us now recall [12] the notion of (one clock) *alternating timed automaton* (OCATA for short). As we will see, OCATA define timed languages, and we will use them to express the semantics of MITL formula. Let $\Gamma(L)$ be a set of formulas defined by the following grammar:

$$\gamma := \top \mid \perp \mid \gamma_1 \vee \gamma_2 \mid \gamma_1 \wedge \gamma_2 \mid \ell \mid x \bowtie c \mid x.\gamma$$

where $c \in \mathbb{N}$, $\bowtie \in \{<, \leq, >, \geq\}$ and $\ell \in L$. We call $x \bowtie c$ a *clock constraint*. Intuitively, the expression $x.\gamma$ means that clock x must be reset to 0.

Definition 2 ([12]). *A **one-clock alternating timed automaton** (OCATA) is a tuple $\mathcal{A} = (\Sigma, L, \ell_0, F, \delta)$ where Σ is a finite alphabet, L is a finite set of locations, ℓ_0 is the initial location, $F \subseteq L$ is a set of accepting locations, $\delta : L \times \Sigma \rightarrow \Gamma(L)$ is the transition function.*




Figure 1: OCATA $\mathcal{A}$

We assume that, for all γ_1, γ_2 in $\Gamma(L)$: $x.(\gamma_1 \vee \gamma_2) = x.\gamma_1 \vee x.\gamma_2$, $x.(\gamma_1 \wedge \gamma_2) = x.\gamma_1 \wedge x.\gamma_2$, $x.x.\gamma = x.\gamma$, $x.(x \bowtie c) = 0 \bowtie c$, $x.\top = \top$ and $x.\perp = \perp$. Thus, we can write any formula of $\Gamma(L)$ in disjunctive normal form, and, from now on, we assume that $\delta(\ell, \sigma)$ is written in disjunctive normal form. That is, for all ℓ, σ , we have $\delta(\ell, \sigma) = \bigvee_j \bigwedge_k A_{j,k}$, where each term $A_{j,k}$ is of the form $\ell, x.\ell, x \bowtie c$ or $0 \bowtie c$, with $\ell \in L$ and $c \in \mathbb{N}$. We call *arc* of the OCATA $\mathcal{A}$ a triple $(\ell, \sigma, \bigwedge_k A_{j,k})$ s.t. $\bigwedge_k A_{j,k}$ is a disjunct in $\delta(\ell, \sigma)$.

Example 2. As an example, consider the OCATA $\mathcal{A}$ in Fig. 1, over the alphabet $\Sigma = \{\sigma\}$. $\mathcal{A}$ has three locations ℓ_0, ℓ_1 and ℓ_2 , such that ℓ_0 is initial and ℓ_0 and ℓ_1 are final. $\mathcal{A}$ has a unique clock x and its transition function is given by : $\delta(\ell_0, \sigma) = \ell_0 \wedge x.\ell_1$, $\delta(\ell_1, \sigma) = (\ell_2 \wedge x = 1) \vee (\ell_1 \wedge x \neq 1)$ and $\delta(\ell_2, \sigma) = \ell_2$. The arcs of $\mathcal{A}$ are thus $(\ell_0, \sigma, \ell_0 \wedge x.\ell_1)$, $(\ell_1, \sigma, \ell_2 \wedge x = 1)$, $(\ell_1, \sigma, \ell_1 \wedge x \neq 1)$ and (ℓ_2, σ, ℓ_2) . Observe that, in the figure we represent the (conjunctive) arc $(\ell_0, \sigma, \ell_0 \wedge x.\ell_1)$ by an arrow splitting in two branches connected resp. to ℓ_0 and ℓ_1 (possibly with different resets: the reset of clock x is depicted by $x := 0$). Intuitively, taking the arc $(\ell_0, \sigma, \ell_0 \wedge x.\ell_1)$ means that, when reading a σ from location ℓ_0 and clock value v , the automaton should start two copies of itself, one in location ℓ_0 , with clock value v , and a second in location ℓ_1 with clock value 0. Both copies should accept the suffix for the word to be accepted. This notion will be defined formally in the next section.

3 An intervals semantics for OCATA

The *standard* semantics for OCATA [11, 9] is defined as an infinite transition system whose *configurations* are finite sets of pairs (ℓ, v) , where ℓ is a location and v is the valuation of the (unique) clock. Intuitively, each configuration thus represents the current state of all the copies (of the unique clock) that run in parallel in the OCATA. The transition system is *infinite* because one cannot bound, a priori, the number of different clock valuations that can appear in a single configuration, thereby requiring peculiar techniques, such as well-quasi orderings (see [12]) to analyse it. In this section, we introduce a *novel* semantics for OCATA, in which *configurations* are sets of *states* (ℓ, I) , where ℓ is a location of the OCATA and I is an *interval*, instead of a single point in $\mathbb{R}^+$. Intuitively, a state (ℓ, I) is an abstraction of all the states (ℓ, v) with $v \in I$, in the standard semantics. We further introduce the notion of *approximation function*. Roughly speaking, an approximation function associates with each configuration C (in the interval semantics), a set of configurations that *approximates* C (in a sense that will be made precise later), and *contains less states than* C . In section 4, we will show

that the interval semantics, combined to a proper approximation function, allows us to build, from all MITL formula Φ , an OCATA $\mathcal{A}_\Phi$ accepting $\llbracket \Phi \rrbracket$, and whose *reachable configurations contain a bounded number of intervals*. This will be the basis of our algorithm to build a *timed automaton* recognising Φ (and hence performing automata-based model-checking of MITL).

We call *state* of an OCATA $\mathcal{A} = (\Sigma, L, \ell_0, F, \delta)$ a couple (ℓ, I) where $\ell \in L$ and $I \in \mathcal{I}(\mathbb{R}^+)$. We note $S = L \times \mathcal{I}(\mathbb{R}^+)$ the state space of $\mathcal{A}$. A state (ℓ, I) is *accepting* iff $\ell \in F$. When $I = [v, v]$ (sometimes denoted $I = \{v\}$), we shorten (ℓ, I) by (ℓ, v) . A *configuration* of an OCATA $\mathcal{A}$ is a (possibly empty) finite set of states of $\mathcal{A}$ whose intervals associated to a same location are disjoint. In the rest of the paper, we sometimes see a configuration C as a function from L to $2^{\mathcal{I}(\mathbb{R}^+)}$ s.t. for all $\ell \in L$: $C(\ell) = \{I \mid (\ell, I) \in C\}$. We note $\text{Config}(\mathcal{A})$ the set of all configurations of $\mathcal{A}$. The *initial configuration* of $\mathcal{A}$ is $\{(\ell_0, 0)\}$. A configuration is *accepting* iff all the states it contains are accepting (in particular, the empty configuration is accepting). For a configuration C and a delay $t \in \mathbb{R}^+$, we note $C+t$ the configuration $\{(\ell, I+t) \mid (\ell, I) \in C\}$. From now on, we assume that, for all configurations C and all locations ℓ : when writing $C(\ell)$ as $\{I_1, \dots, I_m\}$ we have $I_i < I_{i+1}$ for all $1 \leq i < m$. Let E be a finite set of intervals from $\mathcal{I}(\mathbb{R}^+)$. We let $\|E\| = |\{[a, a] \in E\}| + 2 \times |\{I \in E \mid \inf(I) \neq \sup(I)\}|$ denote the *number of clock copies* of E . Intuitively, $\|E\|$ is the number of *individual clocks* we need to encode all the information present in E , using one clock to track singular intervals, and two clocks to retain $\inf(I)$ and $\sup(I)$ respectively for non-singular intervals I . For a configuration C , we let $\|C\| = \sum_{\ell \in L} \|C(\ell)\|$.

Interval semantics. Our definition of the *interval semantics* for OCATA follows the definition of the *standard semantics* as given by Ouaknine and Worrell [11], adapted to cope with intervals. Let $M \in \text{Config}(\mathcal{A})$ be a configuration of an OCATA $\mathcal{A}$, and $I \in \mathcal{I}(\mathbb{R}^+)$. We define the satisfaction relation " $\models_I$ " on $\Gamma(L)$ as:

$$\begin{array}{llll} M \models_I \top & & M \models_I \ell & \text{iff } (\ell, I) \in M \\ M \models_I \gamma_1 \wedge \gamma_2 & \text{iff } M \models_I \gamma_1 \text{ and } M \models_I \gamma_2 & M \models_I x \bowtie c & \text{iff } \forall x \in I, x \bowtie c \\ M \models_I \gamma_1 \vee \gamma_2 & \text{iff } M \models_I \gamma_1 \text{ or } M \models_I \gamma_2 & M \models_I x.\gamma & \text{iff } M \models_{[0,0]} \gamma \end{array}$$

We say that M is a *minimal model* of the formula $\gamma \in \Gamma(L)$ with respect to the interval $I \in \mathcal{I}(\mathbb{R}^+)$ iff $M \models_I \gamma$ and there is no $M' \subsetneq M$ such that $M' \models_I \gamma$. Remark that a formula γ can admit several minimal models (one for each disjunct in the case of a formula of the form $\gamma = \bigvee_{j,k} \bigwedge A_{j,k}$). Intuitively, for $\ell \in L, \sigma \in \Sigma$ and $I \in \mathcal{I}(\mathbb{R}^+)$,

a minimal model of $\delta(\ell, \sigma)$ with respect to I represents a configuration the automaton can reach from state (ℓ, I) by reading σ . The definition of $M \models_I x \bowtie c$ only allows to take a transition $\delta(\ell, \sigma)$ from state (ℓ, I) if all the values in I satisfy the clock constraint $x \bowtie c$ of $\delta(\ell, \sigma)$.

Example 3. Let us consider again the OCATA of Fig. 1. A minimal model M of $\delta(\ell_1, \sigma)$ with respect to $[1.5, 2]$ must be such that: $M \models_{[1.5, 2]} (\ell_1 \wedge x \neq 1) \vee (\ell_2 \wedge x = 1)$. As $\exists v \in [1.5, 2]$ s.t. $v \neq 1$, it is impossible that $M \models_{[1.5, 2]} x = 1$. However, as $\forall v \in [1.5, 2], v \neq 1, M \models_{[1.5, 2]} x \neq 1$ and so $M \models_{[1.5, 2]} (\ell_1 \wedge x \neq 1) \vee (\ell_2 \wedge x = 1)$ iff $M \models_{[1.5, 2]} \ell_1$, i.e. $(\ell_1, [1.5, 2]) \in M$. So, $\{(\ell_1, [1.5, 2])\}$ is the unique minimal model of $\delta(\ell_1, \sigma)$ wrt $[1.5, 2]$.

Approximation functions. As stated before, our goal is to define a semantics for OCATA that enables to bound the number of clock copies. To this end, we define the notion of approximation function: we will use such functions to reduce the number of clock copies associated with each location in a configuration. An approximation function associates with each configuration C a set of configurations C' s.t. $\|C'(\ell)\| \leq \|C(\ell)\|$ and s.t. the intervals in $C'(\ell)$, cover those of $C(\ell)$, for all ℓ . Then, we define the semantics of an OCATA $\mathcal{A}$ by means of a transition system $\mathcal{T}_{\mathcal{A},f}$ whose definition is parametrised by an approximation function f .

Definition 3. Let $\mathcal{A}$ be an OCATA $\mathcal{A}$. An approximation function is a function $f : \text{Config}(\mathcal{A}) \mapsto 2^{\text{Config}(\mathcal{A})}$ s.t. for all configurations C , for all $C' \in f(C)$, for all locations $\ell \in L$: (i) $\|C'(\ell)\| \leq \|C(\ell)\|$, (ii) for all $I \in C(\ell)$, there exists $J \in C'(\ell)$ s.t. $I \subseteq J$, (iii) for all $J \in C'(\ell)$, there are $I_1, I_2 \in C(\ell)$ s.t. $\inf(J) = \inf(I_1)$ and $\sup(J) = \sup(I_2)$. We note $APP_{\mathcal{A}}$ the set of approximation functions for $\mathcal{A}$.

Definition 4. Let $\mathcal{A}$ be an OCATA and let $f \in APP_{\mathcal{A}}$ be an approximation function. The f -semantics of $\mathcal{A}$ is the transition system $\mathcal{T}_{\mathcal{A},f} = (\text{Config}(\mathcal{A}), \rightsquigarrow, \longrightarrow_f)$ on configurations of $\mathcal{A}$ defined as follows:

- the transition relation $\rightsquigarrow$ takes care of the elapsing of time : $\forall t \in \mathbb{R}^+, C \xrightarrow{t} C'$ iff $C' = C + t$. We let $\rightsquigarrow = \bigcup_{t \in \mathbb{R}^+} \xrightarrow{t}$.
- the transition relation $\longrightarrow_f$ takes care of discrete transitions between locations and of the approximation : $C = \{(\ell_k, I_k)_{k \in K}\} \xrightarrow{\sigma} C'$ iff there exists a configuration $C'' = \bigcup_{k \in K} M_k$ s.t. (i) for all k : M_k is a minimal model of $\delta(\ell_k, \sigma)$ with respect to I_k , and (ii) $C' \in f(C'')$. We let $\longrightarrow_f = \bigcup_{\sigma \in \Sigma} \xrightarrow{\sigma}_f$.

We can now define the accepted language of an OCATA (parametrised by an approximation function f). Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word s.t. $|\theta| = n$, and let $f \in APP_{\mathcal{A}}$ be an approximation function. Let us note $t_i = \tau_i - \tau_{i-1}$ for all $1 \leq i \leq |\theta|$, assuming $\tau_0 = 0$. An f -run of $\mathcal{A}$ on θ is a finite sequence of discrete and continuous transitions in $\mathcal{T}_{\mathcal{A},f}$ that is labelled by θ , i.e. a sequence of the form: $C_0 \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_f C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_2}_f \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_f C_{2n}$. We say that an f -run is *accepting* iff its last configuration C_{2n} is accepting and we say that a timed word is f -accepted by $\mathcal{A}$ iff there exists an accepting f -run of $\mathcal{A}$ on this word. We note $L_f(\mathcal{A})$ the language of all finite timed words f -accepted by $\mathcal{A}$. In the rest of the paper, we (sometimes) use the abbreviation $C_i \xrightarrow{t,\sigma}_f C_{i+2}$ for $C_i \xrightarrow{t} C_{i+1} = C_i + t \xrightarrow{\sigma}_f C_{i+2}$.

Observe that this interval semantics generalises the standard OCATA semantics [11]. This standard semantics can be recovered by considering $\mathcal{T}_{\mathcal{A},Id}$, where Id is the approximation function such that $Id(C) = \{C\}$ for all C . Indeed, in $\mathcal{T}_{\mathcal{A},Id}$, all the reachable configurations contain only states of the form $(\ell, [a, a])$, i.e., all intervals are singular. So, each state $(\ell, [a, a])$ can be naturally mapped to a state (ℓ, a) in the standard semantics. From now on, we denote $L_{Id}(\mathcal{A})$ by $L(\mathcal{A})$.

Example 4. Let us consider again the OCATA $\mathcal{A}$ in Fig. 1, and the timed word $\theta = (\sigma, 0)(\sigma, 0.2)(\sigma, 0.5)$, with $|\theta| = 3$. Let f be the approximation function s.t. for all

$C \in \text{Config}(\mathcal{A})$: $f(C) = \{C(\ell_0) \cup C(\ell_2) \cup \{(\ell_1, [\inf(I_1), \sup(I_m)])\}\}$ if $C(\ell_1) = \{I_1, I_2, \dots, I_m\} \neq \emptyset$ (assuming, as mentioned before, that $I_1 < I_2 < \dots < I_m$); and $f(C) = \{C\}$ if $C(\ell_1) = \emptyset$. Thus, roughly speaking, $f(C)$ always contains one configuration, which is obtained from C by merging all the intervals in $C(\ell_1)$ and keeping the rest of the configuration untouched. Then, an f -run on θ is: $\rho_1 = \{(\ell_0, 0)\} \xrightarrow{0, \sigma} \{(\ell_0, 0), (\ell_1, 0)\} \xrightarrow{0.2, \sigma} \{(\ell_0, 0.2), (\ell_1, [0, 0.2])\} \xrightarrow{0.3, \sigma} \{(\ell_0, 0.5), (\ell_1, [0, 0.5])\}$. Also, an Id -run on θ is: $\rho_2 = \{(\ell_0, 0)\} \xrightarrow{0, \sigma} \{(\ell_0, 0), (\ell_1, 0)\} \xrightarrow{0.2, \sigma} \{(\ell_0, 0.2), (\ell_1, 0), (\ell_1, 0.2)\} \xrightarrow{0.3, \sigma} \{(\ell_0, 0.5), (\ell_1, 0), (\ell_1, 0.3), (\ell_1, 0.5)\}$. Now, consider the timed word $\theta' = \theta(\sigma, 1.1)$. An Id -run on θ' is $\rho_3 = \rho_2 \xrightarrow{0.6, \sigma} \{(\ell_0, 1.1), (\ell_1, 0), (\ell_1, 0.6), (\ell_1, 0.9), (\ell_1, 1.1)\}$ (hence θ' is Id -accepted by $\mathcal{A}$), but $\mathcal{A}$ has no f -run on θ' . Indeed, letting 0.6 t.u. elapse from ρ_1 's last configuration yields $\{(\ell_0, 1.1), (\ell_1, [0.6, 1.1])\}$ from which no transition can be fired, because $[0.6, 1.1]$ satisfies neither $x \neq 1$ nor $x = 1$, which are the respective guards of the arcs from ℓ_1 .

In the rest of the paper we will rely mainly on approximation functions that enable to bound the number of clock copies in all configurations along all runs of an OCATA $\mathcal{A}$. Let $k \in \mathbb{N}$ be a constant. We say that $f_k \in APP_{\mathcal{A}}$ is a k -bounded approximation function iff for all $C \in \text{Config}(\mathcal{A})$, for all $C' \in f_k(C)$: $\|C'\| \leq k$.

Accepted language and approximations. Let us now study the relationship between the standard semantics of OCATA and the family of semantics obtained when relying on an approximation function that is different from Id . We show that introducing approximations does not increase the accepted language:

Proposition 1. *For all OCATA $\mathcal{A}$, for all $f \in APP_{\mathcal{A}}$: $L_f(\mathcal{A}) \subseteq L(\mathcal{A})$.*

sketch. Let $C_0 \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1} C_2 \xrightarrow{t_2} C_3 \dots \xrightarrow{\sigma_n} C_{2n}$ be an accepting f -run of $\mathcal{A}$ on θ , and let us build, inductively, an accepting Id -run $D_0 \xrightarrow{t_1} D_1 \xrightarrow{\sigma_1} D_2 \xrightarrow{t_2} D_3 \dots \xrightarrow{\sigma_n} D_{2n}$ on θ s.t. the following invariant holds: for all $1 \leq i \leq 2n$, for all $(\ell, [v, v]) \in D_i$, there is $(\ell, I) \in C_i$ s.t. $v \in I$. The base case is trivial since $C_0 = D_0$. For the inductive case, we first observe that the elapsing of time maintains the invariant. Thus, we have to show that each discrete step in the f -run can be simulated by a discrete step in the Id -run that maintains the invariant. A σ labeled discrete step from some configuration C_{2j+1} in the f -run consists in selecting an arc a_s of the form (ℓ, σ, γ) for each $s = (\ell, I)$ in C_{2j+1} , whose guard is satisfied by I . Then, firing all these arcs yields a configuration E , and $C_{2j+2} \in f(E)$. From each $s' = (\ell, [v, v])$ in D_{2j+1} , we fire the arc a_s where $s = (\ell, I)$ is a state in C_{2j+1} s.t. $v \in I$. Such an s exists by induction hypothesis. Since the effects of the arcs are the same, and by properties of the approximation function, we conclude that D_{2j+2} and C_{2j+2} respect the invariant. In particular D_{2n} and C_{2n} respect it, hence D_{2n} is accepting. $\square$

4 From MITL to Timed Automata

In this section, we present our new technique to build, from any MITL formula Φ , a *timed automaton* that accepts $\llbracket \Phi \rrbracket$. Our technique relies on two ingredients. First, we

recall [12] how to build, from all MITL formula Φ , and OCATA $\mathcal{A}_\Phi$ s.t. $L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$. This is not sufficient to obtain a timed automaton, as, in general, the semantics of an OCATA needs an *unbounded* number of clock copies, which prevents us from translating all OCATA into timed automata. The second ingredient is the definition of a family of *bounded approximation functions* f_Φ^* , s.t., for all MITL formula Φ , $L_{f_\Phi^*}(\mathcal{A}_\Phi) = L(\mathcal{A}_\Phi)$. Since each f_Φ^* is a *bounded approximation function*, the number of clock copies in the f_Φ^* -semantics of $\mathcal{A}_\Phi$ is *bounded*, which allows us to build a *timed automaton* $\mathcal{B}_\Phi$ with the same semantics (thus, $\mathcal{B}_\Phi$ accepts $\llbracket \Phi \rrbracket$).

From MITL to OCATA. We begin by recalling¹ [12] how to build, from any MITL formula Φ (in negative normal form), an OCATA $\mathcal{A}_\Phi$ s.t. $L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$. We let $\mathcal{A}_\Phi = (\Sigma, L, \ell_0, F, \delta)$ where: L is the set containing the initial copy of Φ , noted ' Φ_{init} ', and all the formulas of $Sub(\Phi)$ whose outermost connective is ' U ' or ' $\tilde{U}$ '; $\ell_0 = \Phi_{init}$; F is the set of the elements of L of the form $\varphi_1 \tilde{U}_I \varphi_2$. Finally δ is defined² by induction on the structure of Φ :

- $\delta(\Phi_{init}, \sigma) = x.\delta(\Phi, \sigma)$
- $\delta(\varphi_1 \vee \varphi_2, \sigma) = \delta(\varphi_1, \sigma) \vee \delta(\varphi_2, \sigma)$; $\delta(\varphi_1 \wedge \varphi_2, \sigma) = \delta(\varphi_1, \sigma) \wedge \delta(\varphi_2, \sigma)$
- $\delta(\varphi_1 U_I \varphi_2, \sigma) = (x.\delta(\varphi_2, \sigma) \wedge x \in I) \vee (x.\delta(\varphi_1, \sigma) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I))$
- $\delta(\varphi_1 \tilde{U}_I \varphi_2, \sigma) = (x.\delta(\varphi_2, \sigma) \vee x \notin I) \wedge (x.\delta(\varphi_1, \sigma) \vee \varphi_1 \tilde{U}_I \varphi_2 \vee x > \sup(I))$
- $\forall \sigma_1, \sigma_2 \in \Sigma: \delta(\sigma_1, \sigma_2) = \begin{cases} \text{true} & \text{if } \sigma_1 = \sigma_2 \\ \text{false} & \text{if } \sigma_1 \neq \sigma_2 \end{cases}$
- $\forall \sigma_1, \sigma_2 \in \Sigma: \delta(\neg \sigma_1, \sigma_2) = \begin{cases} \text{false} & \text{if } \sigma_1 = \sigma_2 \\ \text{true} & \text{if } \sigma_1 \neq \sigma_2 \end{cases}$
- $\forall \sigma \in \Sigma: \delta(\top, \sigma) = \top$ and $\delta(\perp, \sigma) = \perp$.

To simplify the following proofs, we deviate slightly from that definition, and assume that if a formula of type $\varphi_1 U_I \varphi_2$ or $\varphi_1 \tilde{U}_I \varphi_2$ appears more than once as a sub-formula of Φ , the occurrences of this formula are supposed different and are encoded as different locations. With this definition, we have:

Definition 1 ([12]). *For all MITL formula Φ : $L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$.*

Example 5. *As an example consider the formula $\Phi_1 = \Box(a \Rightarrow \Diamond_{[1,2]}b)$, which is a shorthand for $\perp \tilde{U}_{[0,+\infty)}(a \Rightarrow (\top U_{[1,2]}b))$. The OCATA $\mathcal{A}_{\Phi_1}$ is given in Fig. 2 (left), where the location $\ell_\Box$ corresponds to Φ_1 and the location $\ell_\Diamond$ corresponds to $\top U_{[1,2]}b$. One can check that this automaton follows strictly the above definition, after simplification of the formulas, except that we have remove the Φ_{init} location and used*

¹Remark that in [12], the authors are concerned with MTL, but since MITL is a syntactic fragment of MTL, the procedure applies here.

²Remark that the $x \leq \sup(I)$ and $x > \sup(I)$ conditions in the resp. definitions of $\delta(\varphi_1 U_I \varphi_2, \sigma)$ and $\delta(\varphi_1 \tilde{U}_I \varphi_2, \sigma)$ have been added here for technical reasons. This does not modify the accepted language. Indeed, in [12], these conditions are given in the infinite word semantics of OCATA.




Figure 2: (left) OCATA $\mathcal{A}_{\Phi_1}$ with $\Phi_1 = \Box(a \Rightarrow \Diamond_{[1,2]}b)$. (right) The grouping of clocks.

the $\ell_{\Box}$ location as initial location instead, to enhance readability of the example (this does not modify the accepted language, in the present case). Observe the edge labeled by $b, x \in [1, 2]$ from $\ell_{\Diamond}$, without target state: it depicts the fact that, after simplification: $\delta(\top U_{[1,2]}b, b) = (x \in [1, 2]) \vee (\top U_{[1,2]}b)$. Intuitively, this means that, when the automaton has a copy in location ' $\Diamond$ ' with a clock valuation in $[1, 2]$, the copy can be removed from the automaton, because a minimal model of $x \in [1, 2]$ wrt to a valuation v with $v \in [1, 2]$ is $\emptyset$.

To help us build an intuition of the $f_{\Phi_1}^*$ function, let us consider the *Id*-run ρ_1 of $\mathcal{A}_{\Phi_1}$ on $\theta_1 = (a, 0.1)(a, 0.2)(a, 0.3)(b, 2)$ depicted in Fig. 3. Observe that $\theta_1 \models \Phi_1$, and that ρ_1 's last configuration is indeed accepting. Also note that, as in the example of Fig. 1, the number of clock copies necessary in the *Id*-semantics cannot be bounded. Now, let us discuss the intuition behind $f_{\Phi_1}^*$ by considering θ_1 again. Consider ρ'_1 the run prefix of ρ_1 ending in $\{(\ell_{\Box}, 0.2), (\ell_{\Diamond}, 0), (\ell_{\Diamond}, 0.1)\}$. Clearly, the last configuration of ρ'_1 can be over-approximated by grouping the two clock values 0 and 0.1 into the smallest interval that contains them both, i.e. $[0, 0.1]$. This intuition is compatible with the definition of bounded approximation function, and yields the accepting run ρ''_1 depicted in Fig. 3. Nevertheless, we must be careful when grouping clock copies. Let us consider $\theta_2 = (a, 0.1)(a, 0.2)(a, 1.9)(b, 2)(b, 3) \in \llbracket \Phi_1 \rrbracket$, as witnessed by ρ_2 depicted in Fig. 3. When grouping in the same interval, the three clock copies created in $\ell_{\Diamond}$ (along ρ_2) by the reading of the three a 's (and letting further 0.1 time unit elapse) yields the run prefix of ρ'_2 depicted in Fig. 3 ending in $\{(\ell_{\Box}, 2), (\ell_{\Diamond}, [0.1, 1.9])\}$. From the last configuration of this run, the edge with guard $x \in [1, 2]$ and origin $\ell_{\Diamond}$ cannot be taken. Thus, the only way to extend this prefix is through ρ'_2 (depicted in Fig. 3) which yields a run that does not accept θ_2 . Obviously, by grouping the two clock copies created in $\ell_{\Diamond}$ by the two first a 's, and by keeping the third one apart, one obtains the accepting run ρ''_2 (depicted in Fig. 3). Fig. 2 (right) shows the intuition behind the grouping of clocks. The two first positions (with $\sigma_1 = \sigma_2 = a$) of the word satisfy Φ_1 , because of the b in position 4 (with $\tau_4 = 2$), while position 3 (with $\sigma_3 = a$) satisfies Φ_1 because of the b in position 5 (with $\tau_5 = 3$). This explains why we group the two first copies (corresponding to the two first a 's) and keep the third one apart.

The approximation functions f_{Φ}^* . Let us now formally define the family of *bounded* approximation functions that will form the basis of our translation to timed automata. We first give an *upper bound* $M(\Phi)$ on the number of clock copies (intervals) we need to consider in the configurations to recognise an MITL formula Φ . The precise definition of the bound $M(\Phi)$ is technical and is given by induction on the structure of




Figure 3: Several OCATA runs.

the formula. It can be found in the appendix. However, for all MITL formula Φ :

$$M(\Phi) \leq |\Phi| \times \max_{I \in \mathcal{I}_\Phi} \left(4 \times \left\lceil \frac{\inf(I)}{|I|} \right\rceil + 2, 2 \times \left\lceil \frac{\sup(I)}{|I|} \right\rceil + 2 \right)$$

where $\mathcal{I}_\Phi$ is the set of all the intervals that occur in Φ^3 .

Equipped with this bound, we can define the f_Φ^* function. Throughout this description, we assume an OCATA $\mathcal{A}$ with set of locations L . Let $S = \{(\ell, I_0), (\ell, I_1), \dots, (\ell, I_m)\}$ be a set of states of $\mathcal{A}$, all in the same location ℓ , with, as usual $I_0 < I_1 < \dots < I_m$. Then, we let $\text{Merge}(S) = \{(\ell, [0, \sup(I_1)]), (\ell, I_2), \dots, (\ell, I_m)\}$ if $I_0 = [0, 0]$ and $\text{Merge}(S) = S$ otherwise, i.e., $\text{Merge}(S)$ is obtained from S by *grouping* I_0 and I_1 iff $I_0 = [0, 0]$, otherwise $\text{Merge}(S)$ does not modify S . Observe that, in the former case, if I_1 is not a singleton, then $\|\text{Merge}(S)\| = \|S\| - 1$. Now, we can lift the definition of Merge to configurations. Let C be a configuration of $\mathcal{A}$ and let $k \in \mathbb{N}$. We let:

$$\text{Merge}(C, k) = \{C' \mid \|C'\| \leq k \text{ and } \forall \ell \in L : C'(\ell) \in \{\text{Merge}(C(\ell)), C(\ell)\}\}$$

Observe that $\text{Merge}(C, k)$ is a (possibly empty) *set of configurations*, where each configuration (i) has at most k clock copies, and (ii) can be obtained by applying (if possible) or not the Merge function to each $C(\ell)$. Let us now define a family of k -bounded approximation functions, based on Merge . Let $k \geq 2 \times |L|$ be a bound and let C be a configuration, assuming that $C(\ell) = \{I_1^\ell, \dots, I_{m_\ell}^\ell\}$ for all $\ell \in L$. Then:

$$F^k(C) = \begin{cases} \text{Merge}(C, k) & \text{If } \text{Merge}(C, k) \neq \emptyset \\ \{(\ell, [\inf(I_1^\ell), \sup(I_{m_\ell}^\ell)]) \mid \ell \in L\} & \text{otherwise} \end{cases}$$

³The first component of the maximum comes from U and the second from $\tilde{U}$.

Roughly speaking, the $F^k(C)$ function tries to obtain configurations C' that approximate C and s.t. $\|C'\| \leq k$, using the Merge function. If it fails to, i.e., when $\text{Merge}(C, k) = \emptyset$, $F^k(C)$ returns a single configuration, obtained from C by grouping all the intervals in each location. The latter case occurs in the definition of F^k for the sake of completeness. When the OCATA $\mathcal{A}$ has been obtained from an MITL formula Φ , and for k big enough (see hereunder) each $\theta \in \llbracket \Phi \rrbracket$ will be recognised by at least one F^k -run of $\mathcal{A}$ that traverses only configurations obtained thanks to Merge. We can now finally define f_Φ^* for all MITL formula Φ , by letting $f_\Phi^* = F^K$, where $K = \max\{2 \times |L|, M(\Phi)\}$. It is easy to observe that f_Φ^* is indeed a *bounded approximation function*. Then, we can show that, for all MITL formula Φ , the f_Φ^* -semantics of $\mathcal{A}_\Phi$ accepts exactly $\llbracket \Phi \rrbracket$. To obtain this result, we rely on the following proposition⁴:

Proposition 2. *Let Φ be an MITL formula, let K be a set of index and, $\forall k \in K$, let $\Phi_k = \varphi_{1,k} U_{I_k} \varphi_{2,k}$ be subformulas of Φ . For all $k \in K$, let ℓ_{Φ_k} be their associated locations in $\mathcal{A}_\Phi$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word and let $J_k \in \mathcal{I}(\mathbb{R}^+)$ be closed intervals. The automaton $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_{\Phi_k}, J_k)_{k \in K}\}$ iff $\forall k \in K, \exists m_k \geq 1 : (\theta, m_k) \models \varphi_2 \wedge \tau_{m_k} \in I_k - \inf(J_k) \wedge \tau_{m_k} \in I_k - \sup(J_k) \wedge \forall 1 \leq m'_k < m_k : (\theta, m'_k) \models \varphi_1$.*

To illustrate this proposition, let us consider $\Phi_2 \equiv \top U_{[2,3]} b$, the associated automaton $\mathcal{A}_{\Phi_2}$ and the timed word $\theta = (a, 0)(b, 1)(b, 2)$. Assume that $\mathcal{A}_{\Phi_2}$ is in configuration $C = \{(\ell_{\Phi_2}, [0, 2])\}$ and we must read θ from C . Observe that for all value $y \in [0, 2]$, there is a position m in θ s.t. $\tau_m \in [2, 3] - y$ (i.e., τ_m satisfies the temporal constraint of the modality), $(\theta, m) \models b$ and all intermediate positions satisfy $\top$: $\forall 1 \leq m' < m, (\theta, m') \models \top$. In other words, $\forall y \in [0, 2], (\theta, 1) \models \top U_{[2,3]-y} b$. Yet, the conditions of the propositions are not satisfied and, indeed, there is no accepting Id-run of $\mathcal{A}_{\Phi_2}$ from C . Indeed, after reading the first (resp. second) b , the resulting configuration contains $(\ell_{\Phi_2}, [1, 3])$ (resp. $(\ell_{\Phi_2}, [2, 4])$). In both cases, the interval associated to ℓ_{Φ_2} does not satisfy the clock constraint $x \in [2, 3]$ of the transition $x.\delta(\top, b) \wedge x \in [2, 3]$ of $\mathcal{A}_{\Phi_2}$ that enables to leave location ℓ_{Φ_2} . This example also shows that Proposition 2 cannot be obtained as a corollary of the results by Ouaknine and Worrell [12] and deserves a dedicated proof as part of our contribution.

The property given by Proposition 2 is thus crucial to determine, given an accepting run, whether we can *group* several intervals and retain an accepting run or not. This observation will be central to the proof of our main theorem:

Definition 2. *For all MITL formula Φ , f_Φ^* is a bounded approximation function and $L_{f_\Phi^*}(\mathcal{A}_\Phi) = L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$.*

sketch. By definition, f_Φ^* is a *bounded approximation function*. Hence, by Proposition 1, $L_{f_\Phi^*}(\mathcal{A}_\Phi) \subseteq L(\mathcal{A}_\Phi)$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word in $L(\mathcal{A}_\Phi)$, and let us show that $\theta \in L_{f_\Phi^*}(\mathcal{A}_\Phi)$, by building an accepting f_Φ^* -run ρ' on θ . Since, $\theta \in L(\mathcal{A}_\Phi)$, there is an accepting Id-run ρ of $\mathcal{A}_\Phi$ on θ . We assume that $\rho = C_0 \xrightarrow{\tau_1, \sigma_1}_{Id} C_1 \xrightarrow{\tau_2 - \tau_1, \sigma_2}_{Id} C_2 \dots \xrightarrow{\tau_n - \tau_{n-1}, \sigma_n}_{Id} C_n$.

We build, by induction on the length of ρ , a sequence of runs $\rho_0, \rho_1, \dots, \rho_n$ s.t. for all $0 \leq j \leq n$, $\rho_j = D_0^j \xrightarrow{\tau_1, \sigma_1}_{Id} \dots \xrightarrow{\tau_n - \tau_{n-1}, \sigma_n}_{Id} D_n^j$ is an accepting run on θ with

⁴Stated here for the U modality, a similar proposition holds for $\tilde{U}$.

the following properties: (i) for all $0 \leq k \leq j$: $\|D_k^j\| \leq 4 \times \left\lceil \frac{\inf(I_i)}{|I_i|} \right\rceil + 2$, and (ii) assuming $\tau_0 = 0$: $D_j^j \xrightarrow{\tau_{j+1}-\tau_j, \sigma_j} Id \dots \xrightarrow{\tau_n-\tau_{n-1}, \sigma_n} Id D_n^j$ is an accepting *Id*-run on $\theta^{j+1} = (\sigma_{j+1}\sigma_{j+2} \dots \sigma_n, \tau')$, where $\tau' = (\tau_{j+1} - \tau_j)(\tau_{j+2} - \tau_j) \dots (\tau_n - \tau_j)$, assuming $\tau_{-1} = 0$, i.e., θ^j is the suffix of length $n - j$ of θ , where all the timed stamps have been decreased by τ_j . Clearly, letting $\rho_0 = \rho$ satisfied these properties. We build ρ_{k+1} from ρ_k , by first letting $D_0^{k+1}, D_1^{k+1}, \dots, D_k^{k+1} = D_0^k, D_1^k, \dots, D_k^k$, and then showing how to build D_{k+1}^{k+1} from D_{k+1}^k by merging intervals. Let $\ell \in L$. We use the criterion given by Proposition 2 to decide when to group intervals in $D_{k+1}^k(\ell)$. Assume $D_{k+1}^k(\ell) = \{J_1, J_2, \dots, J_m\}$. Then:

- If $D_{k+1}^k(\ell)$ is either empty, or a singleton, we let $D_{k+1}^{k+1}(\ell) = D_{k+1}^k(\ell)$.
- Else, if $J_1 \neq [0, 0]$, then the reading of σ_{k+1} has not created a new copy in ℓ and we let $D_{k+1}^{k+1}(\ell) = D_{k+1}^k(\ell)$ too.
- Else, $J_1 = [0, 0]$ and we must decide whether we group this clock copy with J_2 or not. Assume⁵ ℓ corresponds to the sub-formula $\varphi_1 U_I \varphi_2$. Then:
 1. if $\exists m \geq 1$ such that: $(\theta^{k+1}, \tau_m^{k+1}) \models \varphi_2 \wedge \tau_m^{k+1} \in I - \sup(J_2) \wedge \tau_m^{k+1} \in I \wedge \forall 1 \leq m' < m : (\theta^{k+1}, \tau_{m'}^{k+1}) \models \varphi_1$, then, we let $D_{k+1}^{k+1}(\ell) = \text{Merge}(D_{k+1}^k(\ell))$,
 2. else, we let $D_{k+1}^{k+1}(\ell) = D_{k+1}^k(\ell)$.

We finish the construction of ρ_{k+1} by firing, from D_{k+1}^{k+1} the same arcs as in the $D_{k+1}^k D_{k+1}^k \dots D_n^k$ suffix of ρ_k , using the *Id*-semantics. Proposition 2 guarantees that we have grouped the intervals in such a way that this suffix is an *Id*-accepting run on θ^{k+1} . Finally, we let $\rho' = \rho_n$ which is an accepting run on θ . We finish the proof by a technical discussion showing that ρ_n is an f_Φ^* -run. $\square$

From OCATA to timed automata. Let us show how we can now translate $\mathcal{A}_\Phi$ into a *timed automaton* that accepts $\llbracket \Phi \rrbracket$. The crucial point is to define a *bound*, $M(\Phi)$, on the number of clocks that are necessary to recognise models of Φ .

A timed automaton (TA) is a tuple $\mathcal{B} = (\Sigma, L, \ell_0, X, F, \delta)$, where Σ is a finite *alphabet*, L is finite set of *locations*, $\ell_0 \in L$ is the *initial location*, X is a finite set of *clocks*, $F \subseteq L$ is the set of *accepting locations*, and $\delta \subseteq L \times \Sigma \times \mathcal{G}(X) \times 2^X \times L$ is a finite set of *transitions*, where $\mathcal{G}(X)$ denotes the set of *guards on X*, i.e. the set of all finite conjunctions of *clock constraints* on clocks from X . For a transition $(\ell, \sigma, g, r, \ell')$, we say that g is its *guard*, and r its *reset*. A *configuration* of a TA is a pair (ℓ, v) , where $v : X \mapsto \mathbb{R}^+$ is a *valuation* of the clocks in X . We denote by $\text{Config}(\mathcal{B})$ the set of all configurations of $\mathcal{B}$, and we say that (ℓ, v) is *accepting* iff $\ell \in F$. For all $t \in \mathbb{R}^+$, we have (time successor) $(\ell, v) \xrightarrow{t} (\ell', v')$ iff $\ell = \ell'$ and $v' = v + t$ where $v + t$ is the valuation s.t. for all $x \in X$: $(v + t)(x) = v(x) + t$. For all $\sigma \in \Sigma$, we have (discrete successor) $(\ell, v) \xrightarrow{\sigma} (\ell', v')$ iff there is $(\ell, \sigma, g, r, \ell') \in \delta$

⁵when ℓ corresponds to the sub-formula $\varphi_1 \tilde{U}_I \varphi_2$, we use the proposition similar to Proposition 2 for $\tilde{U}$ to decide whether we group J_1 with J_2 or not.

s.t. $v \models g$, for all $x \in r$: $v'(x) = 0$ and for all $x \in X \setminus r$: $v'(x) = v(x)$. We write $(\ell, v) \xrightarrow{t, \sigma} (\ell', v')$ iff there is $(\ell'', v'') \in \text{Config}(\mathcal{B})$ s.t. $(\ell, v) \xrightarrow{t} (\ell'', v'') \xrightarrow{\sigma} (\ell', v')$. A timed word $\theta = (\bar{\sigma}, \bar{\tau})$ with $\bar{\sigma} = \sigma_1 \sigma_2 \cdots \sigma_n$ and $\bar{\tau} = \tau_1 \tau_2 \cdots \tau_n$ is *accepted* by $\mathcal{B}$ iff there is a *run* of $\mathcal{B}$ on θ , i.e. a sequence of configurations $(\ell_1, v_1), \dots, (\ell_n, v_n)$ s.t. for all $0 \leq i \leq n-1$: $(\ell_i, v_i) \xrightarrow{\tau_i - \tau_{i-1}, \sigma_i} (\ell_{i+1}, v_{i+1})$, where v_0 assigns 0 to all clocks, and assuming that τ_{-1} denotes 0. We denote by $L(\mathcal{B})$ the *language* of $\mathcal{B}$, i.e. the set of words accepted by $\mathcal{B}$.

We can now sketch the translation, the full details can be found in Appendix C. Let Φ be an MITL formula, and assume $\mathcal{A}_\Phi = (\Sigma, L^\Phi, \ell_0^\Phi, F^\Phi, \delta^\Phi)$. Let us show how to build the TA $\mathcal{B}_\Phi = (\Sigma, L, \ell_0, X, F, \delta)$ s.t. $L(\mathcal{B}_\Phi) = L_{f_\Phi^*}(\mathcal{A}_\Phi)$. The TA $\mathcal{B}_\Phi$ is built as follows. For a set of clocks X , we let $\text{loc}(X)$ be the set of functions S that associate with each $\ell \in L^\Phi$ a finite sequence $(x_1, y_1), \dots, (x_n, y_n)$ of pairs of clocks from X , s.t. each clock occurs only once in all the $S(\ell)$. Then, $L = \text{loc}(X)$. Observe that L is indeed a finite set. Intuitively, a configuration (S, v) of $\mathcal{B}_\Phi$ encodes the configuration C of $\mathcal{A}_\Phi$ s.t. for all $\ell \in L^\Phi$: $C(\ell) = \{[v(x), v(y)] \mid (x, y) \in S(\ell)\}$. The other components of $\mathcal{B}_\Phi$ are defined as follows. ℓ_0 is s.t. $\ell_0(\ell_0^\Phi) = (x, y)$, where x and y are two clocks arbitrarily chosen from X , and $\ell_0(\ell) = \emptyset$ for all $\ell \in L^\Phi \setminus \{\ell_0^\Phi\}$. X is a set of clocks s.t. $|X| = M(\Phi)$. F is the set of all locations S s.t. $\{\ell \mid S(\ell) \neq \emptyset\} \subseteq F^\Phi$. Finally, δ allows $\mathcal{B}_\Phi$ to simulate the f_Φ^* -semantics of $\mathcal{A}_\Phi$: the non determinism of δ enables to guess which clocks must be grouped to form appropriate intervals (see appendix for all the details).

Definition 3. For all MITL formula Φ , $\mathcal{B}_\Phi$ has $M(\Phi)$ clocks and $O((|\Phi|)^{m \cdot |\Phi|})$ locations, where $m = \max_{I \in \mathcal{I}_\Phi} \left\{ 2 \times \left\lceil \frac{\inf(I)}{|I|} \right\rceil + 1, \left\lceil \frac{\sup(I)}{|I|} \right\rceil + 1 \right\}$.

5 Future works: towards efficient MITL model checking

Let us close this work by several observations that could yield efficient model checking algorithm for MITL. Let $\mathcal{C}$ be a timed automaton, and let Φ be an MITL formula. Obviously, one can perform *automaton-based model checking* by computing a TA $\mathcal{B}_{\neg\Phi}$ accepting $\llbracket \neg\Phi \rrbracket$ (using the technique presented in Section 4, or the technique of [2]), and explore their synchronous product $\mathcal{C} \times \mathcal{B}_{\neg\Phi}$ using classical region-based or zone-based techniques [1]. This approach has an important drawback in practice: the number M of clocks of the $\mathcal{B}_{\neg\Phi}$ TA is usually very high (using our approach or the [2] approach), and the algorithm exploring $\mathcal{C} \times \mathcal{B}_{\neg\Phi}$ will have to maintain data structures (regions or zone) ranging over $N + M$ clocks, where N is the number of clocks of $\mathcal{C}$.

A way to avoid this blow up in the number of clocks is to perform the model-checking using the OCATA $\mathcal{A}_{\neg\Phi}$ (using its $f_{\neg\Phi}^*$ semantics) instead of the TA $\mathcal{B}_{\neg\Phi}$. First, the size of $\mathcal{A}_{\neg\Phi}$ is *linear* in the size of Φ , and is straightforward to build. Second, a configuration of $\mathcal{C} \times \mathcal{A}_{\neg\Phi}$ stores only the clocks that correspond to *active copies* of $\mathcal{A}_{\neg\Phi}$, which, in practice, can be much smaller than the number of clocks of $\mathcal{B}_{\neg\Phi}$. Third, this approach allows to retain the structure of the OCATA in the transition system of $\mathcal{C} \times \mathcal{A}_{\neg\Phi}$, which allows to define *antichain based algorithms* [6], that rely on a *partial order on the state space* to detect redundant states and avoid exploring them. Such

an approach, has been applied in the case of LTL model-checking [5]. It relies crucially on the translation of LTL formulas to *alternating automata*, and yields dramatic improvements in the practical performance of the algorithm.

To obtain such algorithms, we need a *symbolic data structure* to encode the configurations of $\mathcal{C} \times \mathcal{A}_{\neg\Phi}$. Such a data structure can be achieved by lifting, to our *interval semantics*, the technique from [11] that consists in encoding *regions* of OCATA configurations by means of *finite words*. Remark that this encoding differs from the classical regions for TA [1], in the sense that the *word* encoding allows the number of clocks to change along paths of the transition system.

These ideas explain what we believe are the *benefits* of using an OCATA based characterisation of MITL formulas. The precise definition of the model checking algorithm sketched above is the topic of our current research.

References

- [1] R. Alur and D. L. Dill. A theory of timed automata. *Theor. Comput. Sci.*, 126(2):183–235, 1994.
- [2] R. Alur, T. Feder, and T. A. Henzinger. The benefits of relaxing punctuality. *J. ACM*, 43(1):116–146, 1996.
- [3] J. R. Burch, E. M. Clarke, K. L. McMillan, D. L. Dill, and L. J. Hwang. Symbolic model checking: 10^{20} states and beyond. *Inf. Comput.*, 98(2):142–170, 1992.
- [4] E. M. Clarke, O. Grumberg, and D. Peled. *Model checking*. MIT Press, 2001.
- [5] M. De Wulf, L. Doyen, N. Maquet, and J.-F. Raskin. Antichains: Alternative algorithms for LTL satisfiability and model-checking. In *TACAS*, volume 4963 of *LNCS*. Springer, 2008.
- [6] L. Doyen and J.-F. Raskin. Antichain algorithms for finite automata. In *TACAS*, volume 6015 of *LNCS*. Springer, 2010.
- [7] T. A. Henzinger. *The temporal specification and verification of real-time systems*. PhD thesis, Stanford University, 1991.
- [8] R. Koymans. Specifying real-time properties with metric temporal logic. *Real-Time Systems*, 2(4):255–299, 1990.
- [9] S. Lasota and I. Walukiewicz. Alternating timed automata. *ACM Trans. Comput. Log.*, 9(2), 2008.
- [10] O. Maler, D. Nickovic, and A. Pnueli. From mitl to timed automata. In *FORMATS*, volume 4202 of *LNCS*. Springer, 2006.
- [11] J. Ouaknine and J. Worrell. On the decidability of metric temporal logic. In *LICS’05*. IEEE, 2005.
- [12] J. Ouaknine and J. Worrell. On the decidability and complexity of metric temporal logic over finite words. *Logical Methods in Computer Science*, 3(1), 2007.

- [13] M. Y. Vardi and P. Wolper. An automata-theoretic approach to automatic program verification (preliminary report). In *LICS'86*. IEEE, 1986.

A Proof of Proposition 1

Before proving Proposition 1, we make several useful observations about the transition relation of an OCATA. Let δ be the transition function of some OCATA, let ℓ be a location, let σ be a letter, and assume $\delta(\ell, \sigma) = \bigvee_j a_j$, where each a_j is an arc, i.e. a conjunction of atoms of the form: $\ell', x.\ell', x \bowtie c, 0 \bowtie c, \top$ or $\perp$. Then, we observe that each minimal model of $\delta(\ell, \sigma)$ wrt some interval I corresponds to firing one of the arcs a_j from (ℓ, I) . That, each minimal model can be obtained by choosing an arc a_j from $\delta(\ell, \sigma)$, and applying the following procedure. Assume $a_j = \ell_1 \wedge \dots \wedge \ell_n \wedge x.(\ell_{n+1} \wedge \dots \wedge \ell_m) \wedge \varphi$, where φ is a conjunction of clock constraints. Then, a_j is fireable from a minimal model (ℓ, σ) iff $I \models \varphi$ (otherwise, no minimal model can be obtained from a_j). In this case, the minimal model is $\{(\ell_i, I) \mid 1 \leq i \leq n\} \cup \{(\ell_i, [0, 0]) \mid n+1 \leq i \leq m\}$. This generalises to configurations $C = \{(\ell_1, I_1), \dots, (\ell_n, I_n)\}$: successors C' are obtained by selecting a fireable arc from each (ℓ_i, I_i) , and taking the union of the resulting configurations.

Proposition 1. For all OCATA $\mathcal{A}$, for all $f \in APP_{\mathcal{A}}$: $L_f(\mathcal{A}) \subseteq L(\mathcal{A})$.

Proof. Let us consider a timed word $\theta = (\bar{\sigma}, \bar{\tau})$ in $L_f(\mathcal{A})$ and let us show that $\theta \in L(\mathcal{A})$. Let us assume that $|\theta| = n$. Let $\rho = \{(\ell_0, [0, 0])\} \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_f C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_3}_f \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_f C_{2n}$, for $\{(\ell_0, [0, 0])\} = C_0$ be the accepting f -run of $\mathcal{A}$ on θ , with $\{(\ell_0, [0, 0])\} = C_0$ and where C_{2n} is accepting. Let us build, from ρ , an accepting Id -run $\rho' = D_0 \xrightarrow{t_1} D_1 \xrightarrow{\sigma_1}_{Id} D_2 \xrightarrow{t_2} D_3 \xrightarrow{\sigma_2}_{Id} \dots \xrightarrow{t_n} D_{2n-1} \xrightarrow{\sigma_n}_{Id} D_{2n}$ s.t.:

1. $D_0 = \{(\ell_0, [0, 0])\}$,
2. D_{2n} is accepting, and
3. for all $1 \leq i \leq n$, for all $(\ell, [v, v]) \in D_{2i}$ there is $(\ell, I) \in C_{2i}$ s.t. $v \in I$

We build ρ' by induction on the positions along ρ :

Basis : ($i = 0$) Since $D_0 = C_0$, the property holds trivially.

Induction : ($i = k + 1$) The induction hypothesis is that we have built the prefix of ρ' up to D_{2k} , and that, for all $j \leq k$, for all $(\ell, [v, v]) \in D_{2j}$ there is $(\ell, I) \in C_{2j}$ s.t. $v \in I$. Let us show how to build D_{2k+1} and $D_{2(k+1)}$.

- We first take care of the time transition. Let $D_{2k+1} = D_{2k} + t_{k+1}$. Clearly, $D_{2k} \xrightarrow{t_{k+1}} D_{2k+1}$. In ρ , we have $C_{2k} \xrightarrow{t_{k+1}} C_{2k+1}$, and so $C_{2k+1} = C_{2k} + t_{k+1}$. It is straightforward to prove that this maintains the induction hypothesis:

$$\forall(\ell, [v, v]) \in D_{2k+1} : \exists(\ell, I) \in C_{2k+1} : v \in I \quad (1)$$

- We must build D_{2k+2} corresponding to the transition $D_{2k+1} \xrightarrow{\sigma_{k+1}}_{Id} D_{2k+2}$. Let us assume that $D_{2k+1} = \{(\ell_1, [v_1, v_1]), \dots, (\ell_p, [v_p, v_p])\}$ for some p , and let us assume that $C_{2k+1} = \{(\ell'_1, I_1), \dots, (\ell'_q, I_q)\}$ for some q . Let $h : \{1, \dots, p\} \mapsto \{1, \dots, q\}$ be a function s.t. for all $1 \leq j \leq p$: $v_j \in I_{h(j)}$. This function exists, by (1), and we will rely on it to build D_{2k+2} from C_{2k+2} .

In ρ , $C_{2k+1} \xrightarrow{\sigma_{k+1}}_f C_{2k+2}$. Then, $C_{2k+2} \in f(E)$, where $E = \cup_{1 \leq j \leq q} E_j$ and each E_j is a minimal model of $\delta(\ell'_j, \sigma_{k+1})$ with respect to I_j . Each of those minimal models corresponds to an arc starting from ℓ'_j , let us denote this arc by a_j . Remark that, for all j , I_j satisfies the guard of a_j , since ρ is a genuine run.

Then, we let D_{2k+2} be the configuration obtained by taking, for all $1 \leq j \leq p$, the arc $a_{h(j)}$ from $(\ell_j, [v_j, v_j]) \in D_{2k+1}$. Clearly, v_j satisfies the guard g of $a_{h(j)}$, because $v_j \in I_{h(j)}$, by definition of h , and $I_{h(j)}$ satisfies g . It is also easy to check that $D_{2k+2} = \cup_{1 \leq j \leq p} M_j$, where each M_j is a minimal model of $\delta(\ell_j, \sigma_{k+1})$ wrt. $[v_j, v_j]$. Hence, $D_{2k+1} \xrightarrow{Id} D_{2k+2}$. Finally, since we fire the same arcs in both ρ and ρ' , the resets are the same in both cases. By definition of the approximation function, we conclude that C_{2k+1} and D_{2k+2} satisfy the induction hypothesis.

This induction builds the run ρ' and shows that for all $(\ell, [v, v]) \in D_{2n}$, there is $(\ell, I) \in C_{2n}$ s.t. $v \in I$. As ρ is accepting, C_{2n} is an accepting configuration and all the states it contains are accepting, i.e. $\forall (\ell, I) \in C_{2n}, \ell$ is an accepting location. We deduce from this that D_{2n} is an accepting configuration. $\square$

B Proof of Theorem 2

Before proving Theorem 2, we give a precise characterisation of the bound $M(\Phi)$. Let Φ be an MITL formula in negative normal form. We define $M(\Phi)$, thanks to $M^\infty(\Phi)$ and $M^1(\Phi)$ defined as follows

- if $\Phi = \sigma$ or $\Phi = \neg\sigma$ (with $\sigma \in \Sigma$), then $M(\Phi) = 2$ and $M^\infty(\Phi) = M^1(\Phi) = 0$.
- if $\Phi = \varphi_1 \wedge \varphi_2$, then $M(\Phi) = \max\{2, M^1(\varphi_1) + M^1(\varphi_2)\}$, $M^\infty(\Phi) = M^\infty(\varphi_1) + M^\infty(\varphi_2)$ and $M^1(\Phi) = M^1(\varphi_1) + M^1(\varphi_2)$.
- if $\Phi = \varphi_1 \vee \varphi_2$, then $M(\Phi) = \max\{2, M^1(\varphi_1), M^1(\varphi_2)\}$, $M^\infty(\Phi) = \max\{M^\infty(\varphi_1), M^\infty(\varphi_2)\}$ and $M^1(\Phi) = \max\{M^1(\varphi_1), M^1(\varphi_2)\}$.
- if $\Phi = \varphi_1 U_I \varphi_2$, then $M(\Phi) = \max\{2, M^\infty(\varphi_1) + M^1(\varphi_2) + 1\}$, $M^\infty(\Phi) = \left(4 \times \left\lceil \frac{\inf(I)}{|I|} \right\rceil + 2\right) + M^\infty(\varphi_1) + M^\infty(\varphi_2)$ and $M^1(\Phi) = M^\infty(\varphi_1) + M^1(\varphi_2) + 1$.
- if $\Phi = \varphi_1 \tilde{U}_I \varphi_2$, then $M(\Phi) = \max\{2, M_1(\varphi_1) + M_\infty(\varphi_2) + 1\}$, $M_\infty(\Phi) = \left(2 \times \left\lceil \frac{\sup(I)}{|I|} \right\rceil + 2\right) + M_\infty(\varphi_1) + M_\infty(\varphi_2)$ and $M_1(\Phi) = M_1(\varphi_1) + M_\infty(\varphi_2) + 1$.

Then, let us recall useful results from [11, 12] that enable to prove Proposition 2.

Proposition 3 ([11]). *Let $\Phi = \varphi_1 U_I \varphi_2$ or $\Phi = \varphi_1 \tilde{U}_I \varphi_2$ be an MITL formula and ℓ_Φ the associated location in $\mathcal{A}_\Phi$. Let θ be a timed word. The automaton $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_\Phi, 0)\}$ iff $(\theta, 1) \models \Phi$.*

The following corollary directly follows from Proposition 3.

Corollary 1. Let Φ be an MITL formula, let K be a set of index and, $\forall k \in K$ let $\Phi_k = \varphi_{1,k} U_{I_k} \varphi_{2,k}$ or $\Phi_k = \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ be subformulas of Φ . For all $k \in K$, let ℓ_{Φ_k} be the associated locations in $\mathcal{A}_\Phi$. Let θ be a timed word and, for all $k \in K$. Then, $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_{\Phi_k}, 0)_{k \in K}\}$ iff $(\theta, 1) \models \bigwedge_{k \in K} \varphi_{1,k} U_{I_k} \varphi_{2,k}$.

Let us now adapt this result to the cases where the automaton reads the word from states of the form (ℓ, v) , with v potentially $\neq 0$:

Lemma 1. Let Φ be an MITL formula, let K be a set of index and, $\forall k \in K$ let $\Phi_k = \varphi_{1,k} U_{I_k} \varphi_{2,k}$ or $\Phi_k = \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ be sub-formulas of Φ . For all $k \in K$, let ℓ_{Φ_k} be their associated locations in $\mathcal{A}_\Phi$. Let θ be a timed word and $v_k \in \mathbb{R}^+$ ($\forall k \in K$). The automaton $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_{\Phi_k}, v_k)_{k \in K}\}$ iff $(\theta, 1) \models \bigwedge_{k \in K} (\Phi_k - v_k)$, where, for all $k \in K$, $\Phi_k - v_k$ denotes the formula obtained from Φ_k by replacing the I_k interval on the modality by $I_k - v_k$.

Proof. We prove that, for all $k \in K$ s.t. the outer modality of Φ_k is U : $\mathcal{A}_\Phi$ Id-accepts θ from (ℓ_{Φ_k}, v_k) iff $\theta \models \varphi_{1,k} U_{I_k - v_k} \varphi_{2,k}$. The same arguments adapt to the $\tilde{U}$ case, and the Lemma follows.

Assume $\theta = (\bar{\sigma}, \bar{\tau})$ with $\bar{\sigma} = \sigma_1 \sigma_2 \dots \sigma_n$ and $\bar{\tau} = \tau_1 \tau_2 \dots \tau_n$. For all $v \in \mathbb{R}^+$, let $\theta + v$ denote the timed word $(\bar{\sigma}, \tau')$, where $\tau' = (\tau_1 + v)(\tau_2 + v) \dots (\tau_n + v)$. Observe that, by definition of the semantics of MITL, $\theta \models \varphi_1 U_I \varphi_2$ iff $\theta + v \models \varphi_1 U_{I+v} \varphi_2$ (remark that the φ_1 and φ_2 formulas are preserved).

First, assume that $\theta \models \varphi_{1,k} U_{I_k - v_k} \varphi_{2,k}$ and let us show that $\mathcal{A}_\Phi$ Id-accepts θ from (ℓ_{Φ_k}, v_k) . Since $\theta \models \varphi_{1,k} U_{I_k - v_k} \varphi_{2,k}$, $\theta + v_k \models \varphi_{1,k} U_{I_k} \varphi_{2,k} \equiv \Phi_k$. Then, by Proposition 3, $\mathcal{A}_\Phi$ Id-accepts $\theta + v_k$ from $(\ell_{\Phi_k}, 0)$. Let $(\ell_{\Phi_k}, 0) \xrightarrow{\tau_1 + v_k, \sigma_1}_{Id} C_1 \xrightarrow{\tau_2 - \tau_1, \sigma_2}_{Id} \dots \xrightarrow{\tau_n - \tau_{n-1}, \sigma_n}_{Id} C_n$ be an accepting Id-run of $\mathcal{A}_\Phi$ from $(\ell_{\Phi_k}, 0)$ on $\theta + v_k$. Obviously, the first time step can be decomposed as follows: $(\ell_{\Phi_k}, 0) \xrightarrow{v_k}_{Id} (\ell_{\Phi_k}, v_k) \xrightarrow{\tau_1, \sigma_1}_{Id} C_1 \xrightarrow{\tau_2 - \tau_1, \sigma_2}_{Id} \dots \xrightarrow{\tau_n - \tau_{n-1}, \sigma_n}_{Id} C_n$, where the prefix starting in (ℓ_{Φ_k}, v_k) is an accepting Id-run on θ . We conclude that $\mathcal{A}_\Phi$ Id-accepts θ from (ℓ_{Φ_k}, v_k) .

By using the same arguments, we can prove that $\mathcal{A}_\Phi$ Id-accepts θ from (ℓ_{Φ_k}, v_k) implies that $\theta \models \varphi_{1,k} U_{I_k - v_k} \varphi_{2,k}$. $\square$

Let us show that Lemma 1 extends to non singular intervals:

Lemma 2. Let Φ be an MITL formula, let K a set of index and, $\forall k \in K$, let Φ_k be subformulas of Φ of the form either $\varphi_{1,k} U_{I_k} \varphi_{2,k}$ or $\varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$. For all $k \in K$, let ℓ_{Φ_k} be their associated locations in $\mathcal{A}_\Phi$. Let θ be a timed word and $J_k \in \mathcal{I}(\mathbb{R}^+)$ ($\forall k \in K$). The automaton $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_{\Phi_k}, J_k)_{k \in K}\}$ iff $\forall k \in K$, $\mathcal{A}_\Phi$ Id-accepts θ from configuration $\{(\ell_{\Phi_k}, J_k)\}$.

Proof. It is straightforward by definition of runs on $\mathcal{A}_\Phi$: the time elapsed is reported on each state (ℓ_{Φ_k}, J_k) and the reading of a letter gives a minimal model for each state (ℓ_{Φ_k}, J_k) before to merge them into a unique new configuration. $\square$

Now, we recall a result from [12]:

Lemma 3 ([12]). Let Φ be an MITL formula and φ a sub-formula of Φ . Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word and $\rho : C_0 = \{(\ell_\Phi, 0)\} \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_{Id} C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_2}_{Id} \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_{Id} C_{2n}$ an accepting *Id*-run of $\mathcal{A}_\Phi$ on θ . $\forall 1 \leq i \leq n$, if $C_{2i} \models_{[0,0]} \delta(\varphi, \sigma_i)$, then $(\theta, i) \models \varphi$.

We can now prove Proposition 2.

Proposition 2 : Let Φ be an MITL formula, let K be a set of index and, $\forall k \in K$, let $\Phi_k := \varphi_{1,k} U_{I_k} \varphi_{2,k}$ be sub-formulas of Φ . For all $k \in K$, let ℓ_{Φ_k} be their associated locations in $\mathcal{A}_\Phi$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word and $J_k \in \mathcal{I}(\mathbb{R}^+)$ closed. The automaton $\mathcal{A}_\Phi$ *Id*-accepts θ from configuration $\{(\ell_{\Phi_k}, J_k)_{k \in K}\}$ iff $\forall k \in K$: $\exists m_k \geq 1$: $(\theta, m_k) \models \varphi_2 \wedge \tau_{m_k} \in I_k - \inf(J_k) \wedge \tau_{m_k} \in I_k - \sup(J_k) \wedge \forall 1 \leq m'_k < m_k$: $(\theta, m'_k) \models \varphi_1$.

Proof. Thanks to Lemma 2, we only need to prove the following. Let Ψ be an MITL formula, $\Phi := \varphi_1 U_I \varphi_2$ a sub-formula of Ψ and ℓ_Φ its associated location in $\mathcal{A}_\Psi$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word and $J \in \mathcal{I}(\mathbb{R}^+)$ closed. The automaton $\mathcal{A}_\Psi$ *Id*-accepts θ from configuration $\{(\ell_\Phi, J)\}$ iff $\exists m \geq 1$: $(\theta, m) \models \varphi_2 \wedge \tau_m \in I - \inf(J) \wedge \tau_m \in I - \sup(J) \wedge \forall 1 \leq m' < m$: $(\theta, m') \models \varphi_1$.

($\Rightarrow$) As automaton $\mathcal{A}_\Psi$ *Id*-accepts θ from configuration $\{(\ell_\Phi, J)\}$, there exists an accepting *Id*-run of $\mathcal{A}_\Psi$ on θ from $\{(\ell_\Phi, J)\}$, say

$$\rho = C_0 \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_{Id} C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_2}_{Id} \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_{Id} C_{2n},$$

where $C_0 = \{(\ell_\Phi, J)\}$ and C_{2n} is accepting. For all i , when reading σ_i , two transitions can be taken: either $x.\delta(\varphi_2, \sigma) \wedge x \in I$ or $x.\delta(\varphi_1, \sigma) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$. Let m be the first position in the run where the transition $x.\delta(\varphi_2, \sigma) \wedge x \in I$ is taken. Such a position must exist because ℓ_Φ is not an accepting location but ρ is an accepting *Id*-run. Then, for all $m' < m$, when reading $\sigma_{m'}$, the transition $x.\delta(\varphi_1, \sigma_j) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$ is taken : it does not reset clock copies that stay in ℓ_Φ . So, the part of configuration C_{2m-1} associated with location ℓ_Φ is $\{(\ell_\Phi, J + \tau_m)\}$. As the transition $x.\delta(\varphi_2, \sigma_m) \wedge x \in I$ is then taken, $J + \tau_m$ must satisfy $x \in I$, i.e. (by definition of the minimal model) $\forall v + \tau_m \in J + \tau_m, v + \tau_m \in I$, i.e. : $\forall v \in J, \tau_m \in I - v$ and in particular (as J closed) $\tau_m \in I - \inf(J) \wedge \tau_m \in I - \sup(J)$. Moreover, as ρ is an accepting *Id*-run, the part $x.\delta(\varphi_2, \sigma_m)$ of the transition taken from $\{(\ell_\Phi, J + \tau_m)\}$ corresponds to the fact that $C_{2m} \models_{[0,0]} \delta(\varphi_2, \sigma_m)$, thanks to Lemma 3, we know it means that $(\theta, m) \models \varphi_2$. In the same way, with the reading of $\sigma_{m'}$, for $1 \leq m' < m$, the transition $x.\delta(\varphi_1, \sigma_{m'}) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$ was taken. As ρ is an accepting *Id*-run, the part $x.\delta(\varphi_1, \sigma_{m'})$ of the transition taken from $\{(\ell_\Phi, J + \tau_m)\}$ corresponds to the fact that $C_{2m'} \models_{[0,0]} \delta(\varphi_1, \sigma_{m'})$, thanks to Lemma 3, we know it means that $(\theta, m') \models \varphi_1$. We conclude that $\exists m \geq 1$: $(\theta, m) \models \varphi_2 \wedge \tau_m \in I - \inf(J) \wedge \tau_m \in I - \sup(J) \wedge \forall 1 \leq m' < m$: $(\theta, m') \models \varphi_1$.

($\Leftarrow$) In the sequel, we use the following notation. Assume that $\theta = (\bar{\sigma}, \bar{\tau})$, where $\bar{\sigma} = \sigma_1 \sigma_2 \dots \sigma_n$ and $\bar{\tau} = \tau_1 \tau_2 \dots \tau_n$. For all $1 \leq k \leq n$, we denote by $\theta_k = (\bar{\sigma}_k, \bar{\tau}_k)$, where $\bar{\sigma}_k = \sigma_k \sigma_{k+1} \dots \sigma_n$ and $\bar{\tau}_k = \tau'_1 \tau'_2 \dots \tau'_{n-k}$ the timed word such that $\forall 1 \leq i \leq n - k$, $\tau'_i = \tau_{i+k} - \tau_k$.

We will construct an accepting *Id*-run ρ of $\mathcal{A}_\Psi$ on θ from configuration $\{(\ell_\Phi, J)\}$, say

$C_0 = \{(\ell_\Phi, J)\} \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_{Id} C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_2}_{Id} \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_{Id} C_{2n}$, where C_{2n} is accepting. By hypothesis, $\exists m \geq 0$ such that (a) $(\theta, m) \models \varphi_2$, (b) $\tau_m \in I - \inf(J) \wedge \tau_m \in I - \sup(J)$ and (c) $\forall 1 \leq m' < m : (\theta, m') \models \varphi_1$. From ℓ_Φ we have two possible transitions $x.\delta(\varphi_2, \sigma) \wedge x \in I$ and $x.\delta(\varphi_1, \sigma) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$. We construct ρ in way it consists in following the transition $x.\delta(\varphi_1, \sigma_{m'}) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$, $\forall 1 \leq m' < m$, and the transition $x.\delta(\varphi_2, \sigma_m) \wedge x \in I$ reading σ_m . We must prove that ρ is an accepting Id -run of $\mathcal{A}_\Psi$ on θ .

Remark that following transition $x.\delta(\varphi_1, \sigma_{m'}) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$, $\forall 1 \leq m' < m$, in particular, we loop on Φ without reset of clock. It means that, $\forall 1 \leq m' < m$, $C_{2m'+1}(\ell_\Phi) = \{J + \tau_{m'}\}$. So, it is possible to take transition $x.\delta(\varphi_1, \sigma_{m'}) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$ reading $\sigma_{m'}$ from ℓ_Φ because the interval associated to this location is then $J + \tau_{m'}$ and satisfies the clock constraint $x \leq \sup(I)$: (b) implies that $\tau_{m'} < \tau_m \leq \sup(I) - \sup(J)$, so $\sup(J) + \tau_{m'} \leq \sup(I)$, and so $\forall j + \tau_{m'} \in J + \tau_{m'}, j + \tau_{m'} \leq \sup(I)$. Moreover, we know that $\forall 1 \leq m' < m$, $(\theta, m') \models \varphi_1$. It means that, $\forall 1 \leq m' < m$, the automaton $\mathcal{A}_{\varphi_1}$ Id -accepts $\theta^{m'}$ from $\{(\varphi_{1,init}, 0)\}$, i.e. there is an accepting Id -run of $\mathcal{A}_{\varphi_1}$ on $\theta^{m'}$ taking transition $x.\delta(\varphi_1, \sigma_{m'})$ (the unique transition we can take from location $\varphi_{1,init}$). However, the locations of $\mathcal{A}_{\varphi_1}$ in which leads $x.\delta(\varphi_1, \sigma_{m'})$ can be assimilated to the locations of $\mathcal{A}_\Phi$ corresponding to the same formulas (see definitions of such automata and their locations). So, there is also an accepting run of $\mathcal{A}_\Phi$ on $\theta^{m'}$ taking transition $x.\delta(\varphi_1, \sigma_{m'})$ ($\forall 1 \leq m' < m$). As transitions $x.\delta(\varphi_1, \sigma_{m'}) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I)$ loop on ℓ_Φ , when reading σ_m , the interval $J + \tau_m$ is still associated to location ℓ_Φ . ρ then consists in taking transition $x.\delta(\varphi_2, \sigma_m) \wedge x \in I$. It is possible to take this transition reading σ_m because $J + \tau_m$ satisfies the clock constraint $x \in I$: as $\tau_m \in I - \inf(J) \wedge \tau_m \in I - \sup(J)$ and J is an interval, $\forall j \in J, \tau_m \in I - j$, i.e. $\forall j \in J, j + \tau_m \in I$ and so $\forall v \in J + \tau_m, v \in I$. Moreover, we know that $(\theta, m) \models \varphi_2$. It means that the automaton $\mathcal{A}_{\varphi_2}$ Id -accepts θ^m from $\{(\varphi_{2,init}, 0)\}$, i.e. there is an accepting Id -run of $\mathcal{A}_{\varphi_2}$ on θ^m taking transition $x.\delta(\varphi_2, \sigma_m)$ (the unique transition we can take from location $\varphi_{2,init}$). By the same argument than for φ_1 , there is also an accepting run of $\mathcal{A}_\Phi$ on θ^m taking transition $x.\delta(\varphi_2, \sigma_m)$ which enables to completely construct ρ . $\square$

Proposition 4. Let K be a set of index, $\forall k \in K, \Phi_k := \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ be MITL formulas, ℓ_{Φ_k} the associated locations in an OCATA $\mathcal{A}$ of OW, representing an MITL formula, and $J_k \in \mathcal{I}(\mathbb{R}^+)$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word. The automaton $\mathcal{A}$ Id -accepts θ from configuration $\{(\ell_{\Phi_k}, J_k)_{k \in K}\}$ iff $\forall k \in K, \forall v \in J_k$, the automaton $\mathcal{A}$ accepts θ from configuration $\{(\ell_{\Phi_k}, [v, v])\}$ (i.e. : $\forall k \in K, \forall v \in J_k, (\theta, 1) \models \varphi_{1,k} \tilde{U}_{I_k - v_k} \varphi_{2,k}$).

Proof. Thanks to Lemme 2, we only need to prove the following. Let $\Phi := \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ be MITL formulas, ℓ_Φ the associated location in an OCATA $\mathcal{A}$ of OW, representing an MITL formula, and $J \in \mathcal{I}(\mathbb{R}^+)$. Let $\theta = (\bar{\sigma}, \bar{\tau})$ be a timed word. The automaton $\mathcal{A}$ Id -accepts θ from configuration $\{(\ell_\Phi, J)\}$ iff $\forall v \in J_k$, the automaton $\mathcal{A}$ accepts θ from configuration $\{(\ell_\Phi, [v, v])\}$ (i.e. : $\forall v \in J_k, (\theta, 1) \models \varphi_{1,k} \tilde{U}_{I_k - v_k} \varphi_{2,k}$).
 $(\Rightarrow)$ Let $k \in K$ and $v \in J_k$, we must prove the automaton $\mathcal{A}$ accepts θ from configuration $\{(\ell_\Phi, v)\}$. This proof is similar to proof of Proposition 1, the unique difference is that the initial state D_0 is now $\{(\ell_\Phi, v)\}$.
 $(\Leftarrow)$ We have an accepting Id -run ρ_v of $\mathcal{A}$ on θ from each configuration $\{(\ell_\Phi, v)\}$, say

$C_0^v = \{(\ell_\Phi, v)\} \xrightarrow{t_1} C_1^v \xrightarrow{\sigma_1}_{Id} C_2^v \xrightarrow{t_2} \dots \xrightarrow{t_n} C_{2n-1}^v \xrightarrow{\sigma_n}_{Id} C_{2n}^v$. From the transitions taken along these runs, we can deduce the instants in which $\varphi_{1,k}$ and $\varphi_{2,k}$ are verified (See proof of Lemma 1). We will construct an accepting *Id*-run ρ' of $\mathcal{A}$ on θ from configuration $\{(\ell_\Phi, J_k)\}$, say $C_0 = \{(\ell_\Phi, J_k)\} \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_{Id} C_2 \xrightarrow{t_2} \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_{Id} C_{2n}$. Remark that the six transitions we can take on this run from ℓ_Φ are : " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge x.\delta(\varphi_{1,k}, \sigma_i)$ ", " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ ", " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge x > I_k$ ", " $x \notin I_k \wedge x.\delta(\varphi_{1,k}, \sigma_i)$ ", " $x \notin I_k \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " and " $x \notin I_k \wedge x > I_k$ ". So, as long as a transition containing " $\varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " is taken, the clock present in ℓ_Φ is not reset and the part of configurations C_{2i} associated to ℓ_Φ will be $\{(\ell_\Phi, J_k + \tau_i)\}$ (assuming $\tau_0 = 0$). We distinguish several cases to construct ρ' :

- if $\varphi_{2,k}$ is verified on each reading of a letter in $K := \bigcup_{v \in J} I_k - v$: then ρ' con-

sists of taking the transition " $x \notin I_k \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " on each reading of a letter in an instant $\tau_i < K$. In such instants, the part of configuration associated to ℓ_Φ we are in is $\{(\ell_\Phi, J_k + \tau_i)\}$ and we well satisfy $\forall u \in J_k + \tau_i, u \notin I_k$; else $\exists u \in J_k + \tau_i$ such that $u \in I$ and so $u - \tau_i \in J_k$ and $u - (u - \tau_i) = \tau_i \in K$, what contradict our hypothesis. On the other hand, ρ' consists of taking the transition " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " on each reading of a letter in an instant in K . Finally, on the first reading of a letter after K , say in $\tau_j > K$, ρ' consists of taking the transition " $x \notin I_k \wedge x > I_k$ ". It is possible because, then, the part of configuration associated to ℓ_Φ we are in is $\{(\ell_\Phi, J_k + \tau_j)\}$ and $\forall u \in J_k + \tau_j : u > I_k$. To prove it, suppose that $\exists u \in J_k + \tau_j : u < I_k$ or $u \in I_k$. On the first hand, if $u < I_k$, as $u \in J_k + \tau_j$, $\exists v \in J : u = v + \tau_j < I_k$, i.e. : $\exists v \in J : \tau_j < I_k - v$, what contradicts that $\tau_j > K$. On the second hand, if $u \in I_k$, as $u \in J_k + \tau_j$, $\exists v \in J_k : u = v + \tau_j \in I_k$, i.e. : $\exists v \in J_k : \tau_j \in I_k - v$, what contradicts that $\tau_j > K$. ρ' is accepting thanks to the hypothesis of this case.

- else, $\varphi_{1,k}$ is verified in a certain instant in $L = \{u' | \exists u \in K : 0 \leq u' \leq u\}$. Then, there exists a smallest instant $\tau_i \in L$ such that φ_1 is satisfied in τ_i . Moreover, as for each $v \in J_k, (\theta, 1) \models \varphi_{1,k} \tilde{U}_{I_k - v} \varphi_{2,k}$, each instant τ_j with $0 \leq j \leq i$ and $\tau_j \in K$ is an instant in which φ_2 must be satisfied. We must again distinguish two cases:

- If $\tau_i < K$, then ρ' consists of taking the transition " $x \notin I_k \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " on each reading of a letter in an instant τ_j with $0 \leq j < i$ (in such instants, we well satisfy $\forall u \in J_k + \tau_j, u \notin I_k$ because $\tau_j \notin K$) and taking the transition " $x \notin I_k \wedge x.\delta(\varphi_{1,k}, \sigma_i)$ " with the reading of σ_i (it is possible because $\tau_i \notin K$). This run is accepting because the transitions chosen only verify the satisfaction of $\varphi_{1,k}$ in an instant in which we know this formula is verified.
- If $\tau_i \in K$, then ρ' consists of : taking the transition " $x \notin I_k \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " on each reading of a letter in an instant τ_j with $0 \leq j < i$ and $\tau_j \notin K$ (in such instants, we well satisfy $\forall u \in J_k + \tau_j, u \notin I_k$ because $\tau_j \notin K$) ; taking the transition " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge \varphi_{1,k} \tilde{U}_{I_k} \varphi_{2,k}$ " on each reading of a letter in an instant τ_j with $0 \leq j < i$ and $\tau_j \in K$ (we know $\varphi_{2,k}$ is verified

in such instants) and taking the transition " $x.\delta(\varphi_{2,k}, \sigma_i) \wedge x.\delta(\varphi_{1,k}, \sigma_i)$ " with the reading of σ_i (it is possible because as $\tau_i \in K$, $\varphi_{2,k}$ is satisfied in this instant). This run is accepting because the transitions chosen always verify the satisfaction of $\varphi_{1,k}$, or $\varphi_{2,k}$, in instants in which we know these formulas are verified.

□

Thanks to the previous results, we can now prove Theorem 2. We first recall the definition of $\text{Merge}(S)$. Let $S = \{(\ell, I_0), (\ell, I_1), \dots, (\ell, I_m)\}$ be a set of states of $\mathcal{A}$, all in the same location ℓ , with, as usual $I_0 < I_1 < \dots < I_m$. Then, we let $\text{Merge}(S) = \{(\ell, [0, \sup(I_1)]), (\ell, I_2), \dots, (\ell, I_m)\}$ if $I_0 = [0, 0]$ and $\text{Merge}(S) = S$ otherwise, i.e., $\text{Merge}(S)$ is obtained from S by *grouping* I_0 and I_1 iff $I_0 = [0, 0]$, otherwise $\text{Merge}(S)$ does not modify S .

Theorem 2 : For all MITL formula Φ , f_Φ^* is a bounded approximation function and $L_{f_\Phi^*}(\mathcal{A}_\Phi) = L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$.

Proof. The definition of f_Φ^* guarantees it is a bounded approximation function. The equality $L(\mathcal{A}_\Phi) = \llbracket \Phi \rrbracket$ have already been established and Theorem 1 proves the inclusion $L_{f_\Phi^*}(\mathcal{A}_\Phi) \subseteq L(\mathcal{A}_\Phi)$. In the sequel, we so present a prove of the last needed inclusion : $L_{f_\Phi^*}(\mathcal{A}_\Phi) \supseteq L(\mathcal{A}_\Phi)$.

Let $\theta = (\bar{\sigma}, \bar{\tau}) \in L(\mathcal{A}_\Phi)$. There is an accepting Id -run ρ of $\mathcal{A}_\Phi$ on θ , say $C_0 = \{(\ell_0, 0)\} \xrightarrow{t_1} C_1 \xrightarrow{\sigma_1}_{Id} C_2 \xrightarrow{t_2} C_3 \xrightarrow{\sigma_2}_{Id} \dots \xrightarrow{t_n} C_{2n-1} \xrightarrow{\sigma_n}_{Id} C_{2n}$. We must find an f_Φ^* -accepting f_Φ^* -run of $\mathcal{A}_\Phi$ on θ (for $k = \max\{M(\Phi), 2, |L|\}$). Our proof is divided in two parts. In the first one, we will construct an accepting f_θ -run ρ' of $\mathcal{A}_\Phi$ on θ (forming intervals following result of Proposition 2), for a certain approximation function f_θ (later, we will show that f_θ corresponds to f_Φ^*). This run will be $D_0 = \{(\ell_0, J)\} \xrightarrow{t_1} D_1 \xrightarrow{\sigma_1}_{f_\theta} D_2 \xrightarrow{t_2} D_3 \xrightarrow{\sigma_2}_{f_\theta} \dots \xrightarrow{t_n} D_{2n-1} \xrightarrow{\sigma_n}_{f_\theta} D_{2n}$. Simultaneously, we will prove that, the way we group the clock copies with f_θ , each location associated with a formula $\varphi_1 U_I \varphi_2$ will contain at most $4 \cdot \lceil \frac{\inf(I)}{|I|} \rceil + 2$ clock copies all along ρ' . In the second step, we will deduce from the last point that ρ' is an accepting f_Φ^* -run.

In the sequel, we will use the following notation. Assume that $\theta = (\bar{\sigma}, \bar{\tau})$, where $\bar{\sigma} = \sigma_1 \sigma_2 \dots \sigma_n$ and $\bar{\tau} = \tau_1 \tau_2 \dots \tau_n$. For all $1 \leq k \leq n$, we denote by $\theta_k = (\bar{\sigma}_k, \bar{\tau}_k)$, where $\bar{\sigma}_k = \sigma_k \sigma_{k+1} \dots \sigma_n$ and $\bar{\tau}_k = \tau'_1 \tau'_2 \dots \tau'_{n-k}$ the timed word such that $\forall 1 \leq i \leq n-k, \tau'_i = \tau_{i+k} - \tau_k$.

Step 1 : We construct ρ' inductively, using ρ . We reduce the number of clock copies in the configuration reached after each reading of a letter. Our method is to group the last clock copy associated with a location ℓ_i with the previous interval associated with this location if it is possible, i.e. if we still have an accepting run thanks to Proposition 2 (this corresponds to the $\text{Merge}()$ function). In the same time, we will prove that, in each configuration $D = \bigcup_{\ell_i \in L} D(\ell_i)$ reached with ρ' , if ℓ_i corresponds to a formula $\varphi_1 U_{I_i} \varphi_2$, $\|D(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$.

The induction hypothesis (at step $k+1$) is that we have an accepting run on θ :

$$D_0 \xrightarrow{t_1} D_1 \dots D_{2k-1} \xrightarrow{\sigma_k}_{Id} D_{2k} \xrightarrow{t_{k+1}} E_{2k+1} \dots E_{2n-1} \xrightarrow{\sigma_n}_{Id} E_{2n},$$

such that $\forall 0 \leq j \leq 2k, \forall \ell_i \in L$ corresponding to a formula $\varphi_1 U_{I_i} \varphi_2$, we have that $\|D_j(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$ and $D_{2k} \xrightarrow{t_{k+1}} E_{2k+1} \cdots E_{2n-1} \xrightarrow{\sigma_p} E_{2n}$ is an accepting Id -run on θ^{k+1} . Thanks to this hypothesis, we will show how to build

$$D_{2k} \xrightarrow{t_{k+1}} D_{2k+1} \xrightarrow{\sigma_{k+1}} D_{2k+2} \xrightarrow{t_{k+2}} F_{2k+3} \cdots F_{2n-1} \xrightarrow{\sigma_p} F_{2n}$$

such that

- (i) $D_0 \xrightarrow{t_1} D_1 \cdots D_{2k} \xrightarrow{\sigma_k} D_{2k+1} \xrightarrow{\sigma_{k+1}} D_{2k+2} \xrightarrow{t_{k+2}} F_{2k+3} \cdots F_{2n-1} \xrightarrow{\sigma_p} F_{2n}$ is an accepting run on θ ,
- (ii) $\forall \ell_i \in L$ corresponding to a formula $\varphi_1 U_{I_i} \varphi_2 : \|D_{2k+2}(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$,
- (iii) $D_{2k+2} \xrightarrow{t_{k+2}} F_{2k+3} \cdots F_{2n-1} \xrightarrow{\sigma_p} F_{2n}$ is an accepting Id -run on θ^{k+1} .

Basis : (k=0) we define $D_0 = C_0 = \{(\ell_0, [0, 0])\}$. We still have an accepting Id -run of $\mathcal{A}_\Phi$ on $\theta : \rho$. (The number of copies in ℓ_0 will be discussed later because this location does not always correspond to a formula $\varphi_1 U_{I_i} \varphi_2$.)

Induction : (k+1)

We know there is an accepting Id -run of $\mathcal{A}_\Phi$ from D_{2k} on θ^{k+1} , say the two first steps of this Id -run are : $D_{2k} \xrightarrow{t_{k+1}} E_{2k+1} \xrightarrow{\sigma_{k+1}} E_{2(k+1)}$. We define configuration D_{2k+1} of ρ' as $D_{2k+1} := E_{2k+1}$. As $\forall \ell_i \in L$ corresponding to a formula $\varphi_1 U_{I_i} \varphi_2$, $\|D_{2k}(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$ (induction hypothesis), we also have $\|D_{2k+1}(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$. Assume that $E_{2k+2}(\ell_i) = \{J_1^i, \dots, J_{m_i}^i\}$. We define D_{2k+2} of ρ' as $f_\theta(E_{2k+2}) = \bigcup_{\ell_i \in L} f_\theta(E_{2k+2}(\ell_i))$, where $\forall \ell_i \in L$, $f_\theta(E_{2k+2}(\ell_i))$ is defined as follows.

$$f_\theta(E_{2k+2}(\ell_i)) = \begin{cases} \text{Merge}(E_{2k+2}(\ell_i)) & \text{if } \exists m \geq 1 \text{ such that : } (\theta^{k+2}, m) \models \varphi_2 \\ & \wedge \tau'_m \in I_i - \text{sup}(J_2^i) \wedge \tau'_m \in I_i \\ & \wedge (\forall 1 \leq m' < m : (\theta^{k+2}, m') \models \varphi_1) \\ E_{2k+2}(\ell_i) & \text{otherwise} \end{cases}$$

Where, as defined above,

$$\text{Merge}(E_{2k+2}(\ell_i)) = \{(\ell_i, [0, \text{sup}(J_2^i)]), (\ell_i, J_3^i), (\ell_i, J_4^i), \dots, (\ell_i, J_{m_i}^i)\}$$

We must prove there is an accepting Id -run of $\mathcal{A}_\Phi$ from $D_{2(k+1)} = f_\theta(E_{2k+2}) = \bigcup_{\ell_i \in L} f_\theta(E_{2k+2}(\ell_i))$ on θ^{k+2} . Let $\ell_i \in L$, thanks to Proposition 2, it is sufficient to prove that there is an accepting Id -run of $\mathcal{A}_\Phi$ on θ^{k+2} from $D_{2(k+1)}(\ell_i) := f_\theta(E_{2k+2}(\ell_i))$. If $f_\theta(E_{2k+2}(\ell_i)) = E_{2k+2}(\ell_i)$, the accepting Id -run given by induction hypothesis on $E_{2k+2}(\ell_i)$ can always be used. Else,

$$f_\theta(E_{2k+2}(\ell_i)) = \{(\ell_i, [0, \text{sup}(J_2^i)]), (\ell_i, J_3^i), (\ell_i, J_4^i), \dots, (\ell_i, J_{m_i}^i)\}$$

As in this case $E_{2k+2}(\ell_i)$ was $\{(\ell_i, [0, 0]), (\ell_i, J_2^i), (\ell_i, J_3^i), (\ell_i, J_4^i), \dots, (\ell_i, J_{m_i}^i)\}$, the accepting Id -run given by induction hypothesis can be used from $\{(\ell_i, J_3^i),$

$(\ell_i, J_4^i), \dots, (\ell_i, J_{m_i}^i)\} \subseteq f_\theta(E_{2k+2}(\ell_i))$ (thanks to Proposition 2) and we only need to prove there is an accepting Id -run of $\mathcal{A}_\Phi$ on θ^{k+2} from $\{(\ell_i, [0, \sup(J_2^i)])\}$.

As in this case $\exists m \geq 1$ such that : $(\theta^{k+2}, m) \models \varphi_2 \wedge \tau'_m \in I_i - \sup(J_2^i) \wedge \tau'_m \in I_i \wedge (\forall 1 \leq m' < m : (\theta^{k+2}, m') \models \varphi_1)$, we can conclude thanks to Proposition 2.

We must now show that, the way we grouped clock copies with $f_\theta, \forall \ell_i \in L$ corresponding to a formula $\varphi_1 U_{I_i} \varphi_2$, $\|D_{2k+2}(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$. We prove it by contradiction.

Let us suppose that $\|D_{2k+2}(\ell_i)\| > 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$, for a certain location ℓ_i corresponding to formula $\varphi_1 U_{I_i} \varphi_2$. We so have more than $2 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 1$ intervals associated with ℓ_i in D_{2k+2} , i.e : $D_{2k+2}(\ell_i) = \{(\ell_i, J_1^i), (\ell_i, J_2^i), \dots, (\ell_i, J_{m_i}^i)\}$, for a certain $m_i > 2 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 1$. The way we grouped clock copies with f_θ , we know that each interval $J_{m_i}^j$, for $1 \leq j \leq m_i$, satisfies the following property :

$$\begin{aligned} \exists k_j \geq 1 \text{ such that : } & (\theta^{k+1}, k_j) \models \varphi_2 \wedge \tau'_{k_j} \in I_i - \sup(J_j^i) \\ & \wedge \tau'_{k_j} \in I_i - \inf(J_j^i) \wedge (\forall 1 \leq k' < k_j, (\theta^{k+1}, k') \models \varphi_1). \end{aligned} \quad (2)$$

(If it is not the case anymore, ρ' would not be an accepting run.) Moreover, $\forall 1 < j \leq m_i$, we have the following property :

$$\begin{aligned} \forall k_m \geq 1 : & (\theta^{k+1}, k_m) \not\models \varphi_2 \vee \tau'_{k_m} \notin I_i - \sup(J_j^i) \vee \tau'_{k_m} \notin I_i - \sup(J_{j-1}^i) \\ & \vee \exists 1 \leq k' < k_m, (\theta^{k+1}, k') \not\models \varphi_1. \end{aligned} \quad (3)$$

(If it is not the case, $\sup(J_{j-1}^i)$ would have been grouped with J_j^i .)

We first claim that $\forall 3 \leq j \leq m_i, \sup(J_j^i) - \sup(J_{j-2}^i) \geq |I_i|$. We will prove it by contradiction. Let j^* be s.t. $3 \leq j^* \leq m_i$ and suppose that $\sup(J_{j^*}^i) - \sup(J_{j^*-2}^i) < |I_i|$, i.e : $\sup(J_{j^*}^i) < |I_i| + \sup(J_{j^*-2}^i)$. Then $(I_i - \sup(J_{j^*}^i)) \cap (I_i - \sup(J_{j^*-2}^i)) \neq \emptyset$ because these intervals have the same size, moreover, as $\sup(J_{j^*}^i) > \sup(J_{j^*-2}^i)$, $\inf(I_i - \sup(J_{j^*}^i)) < \inf(I_i - \sup(J_{j^*-2}^i))$ and finally : $\sup(I_i - \sup(J_{j^*}^i)) = \sup(I_i) - \sup(J_{j^*}^i) > \sup(I_i) - (|I_i| + \sup(J_{j^*-2}^i)) = \sup(I_i) - \sup(I_i) + \inf(I_i) - \sup(J_{j^*-2}^i) = \inf(I_i) - \sup(J_{j^*-2}^i) = \inf(I_i - \sup(J_{j^*-2}^i))$. So, as $\sup(J_{j^*-2}^i) < \sup(J_{j^*-1}^i) < \sup(J_{j^*}^i)$, $I_i - \sup(J_{j^*-1}^i) \subseteq (I_i - \sup(J_{j^*}^i)) \cup (I_i - \sup(J_{j^*-2}^i))$. Equation (2), letting $j = j^*$ implies that $\tau'_{k_{j^*-1}} \in I_i - \sup(J_{j^*-1}^i)$, so $\tau'_{k_{j^*-1}} \in (I_i - \sup(J_{j^*}^i)) \cup (I_i - \sup(J_{j^*-2}^i))$. Though, if $\tau'_{k_{j^*-1}} \in (I_i - \sup(J_{j^*}^i))$, we contradict (3) in j^* taking $k_m = k_{j^*-1}$ (thanks to the definition of k_{j^*-1}) ; and if $\tau'_{k_{j^*-1}} \in (I_i - \sup(J_{j^*-2}^i))$, we contradict (3) in for $j = j^* - 1$ taking $k_m = k_{j^*-1}$ (thanks to the definition of k_{j^*-1}).

We now know that $\forall 3 \leq j \leq m_i, \sup(J_j^i) - \sup(J_{j-2}^i) \geq |I_i|$. So, $\sup(J_{m_i}^i) -$

$\sup(J_1^i) \geq \lceil \frac{(m_i-2)}{2} \rceil \cdot |I_i|$. As $m_i > 2 \cdot \lceil \frac{\sup(I_i)}{|I_i|} \rceil + 1$, we have that:

$$\begin{aligned} \sup(J_{m_i}^i) - \sup(J_1^i) &> \left\lceil \frac{(2 \cdot \lceil \frac{\sup(I_i)}{|I_i|} \rceil + 1 - 2)}{2} \right\rceil \cdot |I_i| \\ &= \left\lceil \left\lceil \frac{\sup(I_i)}{|I_i|} \right\rceil - \frac{1}{2} \right\rceil \cdot |I_i| = \left\lceil \frac{\sup(I_i)}{|I_i|} \right\rceil \cdot |I_i| \geq \sup(I_i). \end{aligned}$$

It means that $\sup(J_{m_i}^i) - \sup(J_1^i) > \sup(I_i)$, and hence $\sup(J_{m_i}^i) > \sup(I_i)$. It is a contradiction because if $\sup(J_{m_i}^i) > \sup(I_i)$, we can not have an accepting Id -run from $\{(\ell_i, \sup(J_{m_i}^i))\}$ and therefore neither from D_{2k+2} , while we have just proved it is the case.

So far, we have showed that $\forall \ell \in L, \forall 1 \leq j \leq n : \|D_j(\ell_i)\| \leq 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$. So, the bound we have on the run is $|L| \cdot 4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$. In Step 2, we will show we can improve this bound by $M(\Phi)$ and so conclude that our f_θ -run is in fact an f_Φ^* -run.

Case $\varphi_1 \tilde{U}_{I_i} \varphi_2$: The arguments are similar to the U case, using Proposition 4. The bound found is the following : $\forall \ell \in L$ associated to a formula of the form $\varphi_1 \tilde{U}_{I_i} \varphi_2$, $\forall 1 \leq j \leq n : \|D_j(\ell_i)\| \leq 2 \cdot \lceil \frac{\sup(I_i)}{|I_i|} \rceil + 2$. Remark that, to prove this case, we must assume the following property on ρ : for all $0 \leq i \leq 2n$, for all ℓ corresponding to a sub-formula of the form $\varphi_1 \tilde{U}_i \varphi_2$, for all $J \in C_i(\ell)$: $\inf(J) \leq \sup(I)$. Remark that this is always possible, because if an interval J is present in a location ℓ corresponding to $\varphi_1 \tilde{U}_i \varphi_2$, with $\inf(J) > \sup(I)$, the arc $(\ell, \sigma, x \notin I \wedge x > \sup(I))$ can be taken for all $\sigma \in \Sigma$.

Step 2 :

We still must prove that ρ' is an accepting f_Φ^* -run : thanks to Step 1, it remains to prove that each configuration reached by ρ' contains at most $M(\Phi)$ clock copies. By definition of the transitions starting from the initial location $\varphi_{init, \Phi}$, at most two clock copies will be associated with this location (because the initial state is $\{(\ell_0, [0, 0])\}$) and it will have no clock copy associated with this location anymore as soon as clock copies are sent towards other locations. Moreover, all other locations of $\mathcal{A}_\Phi$ are locations associated with sub-formulas of Φ of type $\varphi_1 U_{I_i} \varphi_2$: we know such a location contains at most $4 \cdot \lceil \frac{\inf(I_i)}{|I_i|} \rceil + 2$ clock copies all along ρ' . Remark that the transition starting from the location of a formula $\varphi_1 U_I \varphi_2$ is $(x.\delta(\varphi_2, \sigma) \wedge x \in I) \vee (x.\delta(\varphi_1, \sigma) \wedge \varphi_1 U_I \varphi_2 \wedge x \leq \sup(I))$: it means that $\delta(\varphi_1, \sigma)$ is taken a lot of times while $\delta(\varphi_2, \sigma)$ is only taken once. It is why we distinguish in the definition of $M(\Phi)$ the maximal number of copies present in configurations reached by ρ' : (1) to verify a sub-formula φ of Φ that receives a lot of clock copies (2) to verify a sub-formula φ of Φ that receives at most one clock copy (3) to verify $\varphi = \Phi$, with the complete automaton $\mathcal{A}_\varphi$.

It is not difficult to be convinced that a proof by induction on the structure of Φ enables to show that each configuration of $\mathcal{A}_\Phi$ reached by ρ' contains at most $M(\Phi)$ clock copies.

□

C Towards a timed automaton

Let Φ be an MITL formula, and assume $\mathcal{A}_\Phi = (\Sigma, L^\Phi, \ell_0^\Phi, F^\Phi, \delta^\Phi)$. Let us show how to build the TA $\mathcal{B}_\Phi = (\Sigma, L, \ell_0, X, F, \delta)$ s.t. $L(\mathcal{B}_\Phi) = L_{f_\Phi^*}(\mathcal{A}_\Phi)$. The components of $\mathcal{B}_\Phi$ are as follows. For a set of clocks X , we let $\text{loc}(X)$ be the set of functions S that associate to each $\ell \in L^\Phi$ a finite sequence $(x_1, y_1), \dots, (x_n, y_n)$ of pairs of clocks from X , s.t. each clock occurs only once in all the $S(\ell)$. Then:

- $L = \text{loc}(X)$. Intuitively, a configuration (S, v) of $\mathcal{B}_\Phi$ encodes the configuration C of $\mathcal{A}_\Phi$ s.t. for all $\ell \in L^\Phi$: $C(\ell) = \{[v(x), v(y)] \mid (x, y) \in S(\ell)\}$.
- ℓ_0 is s.t. $\ell_0(\ell_0^\Phi) = (x, y)$, where x and y are two clocks arbitrarily chosen from X , and $\ell_0(\ell) = \emptyset$ for all $\ell \in L^\Phi \setminus \{\ell_0^\Phi\}$.
- X is a set of clocks s.t. $|X| = M(\Phi)$.
- F is the set of all locations S s.t. $\{\ell \mid S(\ell) \neq \emptyset\} \subseteq F^\Phi$.

Finally, we must define the set of transitions δ to let $\mathcal{B}_\Phi$ simulate the executions of $\mathcal{A}_\Phi$. First, we observe that, for each location $\ell \in L^\Phi$, for each $\sigma \in \Sigma$, all arcs in δ^Φ are either of the form $(\ell, \sigma, \text{true})$ or $(\ell, \sigma, \text{false})$ or of the form $(\ell, \sigma, \ell \wedge x.(\ell_1 \wedge \dots \wedge \ell_k) \wedge g)$ or of the form $(\ell, \sigma, x.(\ell_1 \wedge \dots \wedge \ell_k) \wedge g)$, where g is *guard* on x , i.e. a finite conjunction of clock constraints on x . Let $S \in \text{Config}(\mathcal{B}_\Phi)$ be a configuration of $\mathcal{B}_\Phi$, let $\ell \in L^\Phi$, let $\sigma \in \Sigma$ be a letter. Let (x, y) be a pair of clocks occurring in $S(\ell)$ and let us associate to this pair an arc a of δ^Φ of the form (ℓ, σ, γ) . Then, we associate to a a *guard* $\text{guard}(a)$, and two sets $\text{reset}(a)$ and $\text{loop}(a)$, defined as follows:

- if $\gamma \in \{\text{true}, \text{false}\}$, then, $\text{guard}(a) = a$ and $\text{reset}(a) = \text{loop}(a) = \emptyset$.
- if γ is of the form $x.(\ell_1 \wedge \dots \wedge \ell_k) \wedge g$, then $\text{guard}(a) = g$, $\text{reset}(a) = \{\ell_1, \dots, \ell_k\}$ and $\text{loop}(a) = \emptyset$.
- if γ is of the form $\ell \wedge x.(\ell_1 \wedge \dots \wedge \ell_k) \wedge g$, then $\text{guard}(a) = g$, $\text{reset}(a) = \{\ell_1, \dots, \ell_k\}$ and $\text{loop}(a) = \{(x, y)\}$.

Thanks to those definitions, we can now define δ . Let S be a location in L , and assume:

$$\{(\ell_1, x_1, y_1), \dots, (\ell_k, x_k, y_k)\} = \{(\ell, x, y) \mid (x, y) \in S(\ell)\}$$

Then $(S, \sigma, g, r, S') \in \delta$ iff there are: a set $A = \{a_1, \dots, a_k\}$ of arcs s.t.:

- for all $1 \leq i \leq k$: a_i is an arc of δ^Φ of the form (ℓ, σ, γ_k) , associated to (x_i, y_i) .
- For each $\ell \in L^\Phi$, we let $\bar{S}_\ell = (x'_1, y'_1)(x'_2, y'_2) \dots (x'_m, y'_m)$ be obtained from $S(\ell)$ by deleting all pairs $(x, y) \notin \bigcup_{1 \leq i \leq k} \text{loop}(a_i)$. Then, for all $\ell \in L^\Phi$:

$$S'(\ell) \in \{(x, y) \cdot \bar{S}_\ell, (x, y'_1)(x'_2, y'_2) \dots (x'_m, y'_m)\} \quad \text{if } \ell \in \bigcup_{1 \leq i \leq k} \text{reset}(a_i)$$

$$S'(\ell) = \bar{S}_\ell \quad \text{otherwise}$$

When $S'(\ell) = (x, y) \cdot \bar{S}_\ell$, we let $R_\ell = \{x, y\}$; when $S'(\ell) = (x, y'_1)(x'_2, y'_2) \dots (x'_m, y'_m)$, we let $R_\ell = \{x\}$; and we let $R_\ell = \emptyset$ otherwise.

- $g = \bigwedge_{1 \leq i \leq k} (\text{guard}(a_i) [x/x_i] \wedge \text{guard}(a_i) [x/y_i]).$
- $r = \bigcup_{\ell \in L} R_\ell.$

For all MITL formula Φ , let $\mathcal{I}_\Phi$ be the set of all the intervals that occur in Φ . Then:

Theorem 3: For all MITL formula Φ , $\mathcal{B}_\Phi$ has $M(\Phi)$ clocks and $O((|\Phi|)^{m \cdot |\Phi|})$ locations, where $m = \max_{I \in \mathcal{I}_\Phi} \left\{ 2 \times \left\lceil \frac{\inf(I)}{|I|} \right\rceil + 1, \left\lceil \frac{\sup(I)}{|I|} \right\rceil + 1 \right\}.$

Proof. By definition of $\mathcal{B}_\Phi$, $|X| = M(\Phi) = O(2.m.|\Phi|)$. Moreover, one location of this automaton is an association, to each location ℓ of $\mathcal{A}_\Phi$, of a finite sequence $(x_1, y_1), \dots, (x_n, y_n)$ of pairs of clocks from X such that each pair is associated to a unique ℓ . In other words, each couple of clocks (x_i, y_i) can be associated to : either one and only one of the $\ell \in L$ or to no $\ell \in L$. We so have $|L| + 1$ possibilities of association of each pair (x_i, y_i) and we have $\frac{M(\Phi)}{2}$ such pairs. So, $\mathcal{B}_\Phi$ has $(|L| + 1)^{\frac{M(\Phi)}{2}}$ locations, i.e. : $O((|\Phi|)^{m \cdot |\Phi|}) = O(2^{m \cdot |\Phi| \cdot \log_2(|\Phi|)})$ (because $|L| = O(|\Phi|)$ and $M(\Phi) = O(2.m.|\Phi|)$).

We prove that $\mathcal{B}_\Phi$ recognizes $\llbracket \Phi \rrbracket$ by mapping each configuration of $\mathcal{B}_\Phi$ to a configuration of $\mathcal{A}_\Phi$ and conversely and that this mapping is consistent with all runs.

First, let (S, v) be a configuration of $\mathcal{B}_\Phi$, we map it to the following configuration of $\mathcal{A}_\Phi$. We know that $\forall \ell \in L$, $S(\ell)$ is a finite sequence $(x_1, y_1), \dots, (x_n, y_n)$ of pairs of clocks from : it corresponds to the (unique) configuration of $\mathcal{A}_\Phi$, $C = \bigcup_{\ell \in L} C(\ell)$ where $C(\ell) = \{[v(x), v(y)] | (x, y) \in S(\ell)\}$. It is straightforward to see that, if $(S, v) \xrightarrow{t} (S', v')$ and (S, v) is mapped to C , there exists C' such that $C \xrightarrow{t} C'$ and C' is mapped to (S', v') . Moreover, we claim that, if $(S, v) \xrightarrow{\sigma} (S', v')$ and (S, v) is mapped to C , there exists C' such that $C \xrightarrow{\sigma}_{f_\Phi} C'$ and C' is mapped to (S', v') . This holds because, if $(S, v) \xrightarrow{\sigma} (S', v')$, we can use the arc $a \in \delta^\Phi(\ell, \sigma)$ associated $(x, y) \in S(\ell)$ to find a minimal model of the state $(\ell, [v(x), v(y)])$ of C , this way, we reach a configuration C' of $\mathcal{A}_\Phi$ that is mapped to (S', v') thanks to the definition of δ : corresponding clocks are reset in the same time ; we verify the same guards on corresponding clocks ; the configuration we can reach in $\mathcal{B}_\Phi$ corresponds, for each location $\ell \in L$ whose smallest associated interval is $[0, 0]$, to group or not this interval with the second associated with ℓ , what correspond to the configurations of $\mathcal{A}_\Phi$ we can reach from C .

Second, let C be a configuration of $\mathcal{A}_\Phi$, we map it to the set of all (S, v) s.t. for all $\ell \in L$: $C(\ell) = \{I_1^\ell, I_2^\ell, \dots, I_n^\ell\}$ iff $v(x_1) = \inf(I_1), v(y_1) = \sup(I_1), \dots, v(x_n) = \inf(I_n), v(y_n) = \sup(I_n)$. Observe that there are indeed several configurations (S, v) of $\mathcal{B}_\Phi$ that satisfy this definition: they can all be obtained up to clock renaming. To keep a consistence in our runs, we must only choose the corresponding configuration of $\mathcal{B}_\Phi$ such that: once a pair of clocks is associated to an interval I_j of $C(\ell)$, if I_j is still in $C'(\ell)$, the same clocks represents its bounds. In the same way, when an interval I'_j of the form $[0, \sup(I_j)]$ is in $C'(\ell)$, the same clocks represents its bounds. In contrary, when a new interval $I_j (= [0, 0])$ is associated to $C(\ell)$, we can arbitrary choose which unused pair of clocks (x_i, y_i) will represent it. Thanks to this trick, we can proof properties similar those of the first step. $\square$